


Disconnect Switches

Series L7 - Motor Disconnect Switches up to 100A	L2
<i>Handles & Accessories</i>	L10
Series L7 Enclosed Disconnect Switches	L14
<i>Technical Information & Dimensions (Online)</i>	L18
Series L11 - Fusible and Non-Fusible Disconnects 30...1200A	L27
<i>Handles & Accessories</i>	L30
Series L11 Enclosed Disconnect Switches	L35
<i>Application Methods, Technical Information & Dimensions (Online)</i>	L36



Series L7 Motor Disconnect Switches up to 100A

UL508 approved device
“suitable as motor disconnect”

TIP!



To learn the basic differences between control, load and fusible disconnect switches and how to apply them, see our white paper Tech-LMSD in the online library.

Sprecher + Schuh's L7 line incorporates the latest modular design techniques to provide maximum functionality with the fewest number of parts. These rugged switches are compact, reliable and the ideal choice for all disconnect applications including motor disconnects per UL-508 Part III. A device under this UL listing meets the requirements as a motor controller or “at motor disconnect.”

Just the right switch for your application

L7 Disconnect Switches are available in four frame sizes up to 100 amps. The smaller L7s come in six pole models, as well as three pole change-over switches. A full complement of switch handles and accessories including auxiliary contact blocks, ground and neutral terminals make the L7 line broad enough to tackle virtually any disconnect duty.

Meets the toughest safety standards

A generous 9mm gap between open contacts, combined with high short circuit withstand capabilities ensures a minimum probability of welding. All switches are touch safe to IP20, while most switch handles are rated for strong water jets to IP66. Excellent making and breaking characteristics provide a level of safety that, in many cases, exceeds international standards.



Modular, flexible and easy to assemble

The versatile L7 line is fully modular. All accessories snap-on and off without the use of tools, speeding assembly. The L7's modular design minimizes inventory with features such as universal auxiliary contact blocks... virtually every block fits all frame sizes. Both metal and plastic shaft extension systems are available to accommodate most panel depths.


International standards and approvals

L7 Motor Disconnect Switches are UL Listed (UL508, Part III) and CSA approved (C22.2 No. 14). They also carry the CE Mark and meet IEC 947-1, 947-3, as well as IEC 207 requirements. They are approved in virtually every international market.




36mm
(≈1 13/32")

16A



45mm
(≈1 3/4")

25A
32A



54mm
(≈2 1/8")

40A
63A



72mm
(≈2 13/16")

80A
100A

Full range of enclosed disconnects for any job

From “do-it-yourself” to fully assembled, we offer a complete selection of three, four and six pole enclosed disconnects for any industrial application.

The most economical choice is to configure your own design (Figure 1) by selecting one of the non-UL/CSA Ap-

proved ABS or Noryl enclosures from page L17 and completing it with your choice of L7 switch from pages L4 ...L6. These enclosed disconnects are suitable for use in NEMA 4 type applications (not UL Listed).

An assembled version of this enclosed disconnect is available with LA7 three or six poles from page L6 (Figure 2). A broad selection of assembled UL

Enclosed disconnects are available on pages L14 and L15. Painted metal, stainless steel, polyester-fiberglass, and ABS (IP66) enclosures with three, four and six pole disconnect switches are available with all accessories (Figure 3).




Figure 1



Figure 2




Figure 3

How to order L7 motor disconnect switches

A complete L7 Motor Disconnect Switch is ordered with as little as two catalog numbers. The first number specifies the switch body and the second specifies the switch handle assembly. All L7 switch bodies come

standard with a shaft and mounting screws for the switch handle assembly. Accessories such as shaft extensions and auxiliary contact blocks are ordered separately.


First determine the switch you need from pages L4...L6. Then turn to page L8 and L9 to choose a switch handle assembly.

If necessary, see page L12 and L13 to determine the type and length of shaft extension you require.

Auxiliary contact blocks, fourth poles, ground terminals and neutral terminals are found on page L10.

Side Mount Accessories - page L10
Miscellaneous Accessories - page L11

Modular Shaft Extensions (LA only) - page L12
Metal Shaft Extensions (LA only) - page L13



LE Switch Body Assemblies - starting on page L4
LA Switch Body Assemblies - starting on page L6



Switch Handle Assemblies - starting on page L8



L7 Disconnect Switches

Front Mounted 3 Pole Switches - 90° Throw ①②

3 Pole	Plastic		Plastic		Metal	
	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price
3 Pole >	LE7-16-1753	57.52	LE7-25-1753	70.88	LE7-32-1753	74.99
Amp Rating (encl.)	16	25	32	40	63	
UL/CSA	16	25	32	40	63	
IEC/VDE/BS						
3Ø Horsepower	3	5	7.5	10	25	
240V	7.5	10	15	20	25	
480V	10	10	15	20	25	
600V						
1Ø Horsepower	1	1	1	2	3	
120V	2	2	3	3	5	
240V						
Dimension - mm (inches)	63 (2-31/64) - Height 36 (1-27/64) - Width 51 (2-1/64) - Depth ②	63 (2-31/64) - Height 45 (1-49/64) - Width 60 (2-23/64) - Depth ②		72 (2-55/64) - Height 54 (2-1/8) - Width 74 (2-29/32) - Depth ②		

3 Pole	Metal	
	Catalog Num.	Price
3 Pole >	LE7-80-1753	168.46
Amp Rating (encl.)	80	100
UL/CSA	80	100
IEC/VDE/BS		
3Ø Horsepower	25	30
240V	40	50
480V	50	50
600V		
1Ø Horsepower	5	7.5
120V	10	15
240V		
Dimension - mm (inches)	90 (3-35/64) - Height 72 (2-27/32) - Width 90 (3-35/64) - Depth ②	

① Fourth pole side-mounted module available. See page L10.

② Dimension without shaft.

③ Switch Handle position




Front Mounted 3 Pole Changeover Switches and 6 Pole Switches - 90° Throw ①



Changeover (Center OFF) 6 Pole 	 Metal		 Metal		 Metal		 Metal		 Metal	
	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price
Changeover >	LE7-16-3753	97.59	LE7-25-3753	128.40	LE7-32-3753	141.75	LE7-40-3753	177.71	LE7-63-3753	203.38
6 Pole >	LE7-16-1756	115.04	LE7-25-1756	142.78	LE7-32-1756	146.89	LE7-40-1756	186.95	LE7-63-1756	209.54
Amp Rating (encl.)	16		25		32		40		63	
UL/CSA	16		25		32		40		63	
IEC/VDE/BS	16		25		32		40		63	
3Ø Horsepower	3		5		7.5		10		15	
240V	3		5		7.5		10		15	
480V	7.5		10		15		20		25	
600V	10		10		15		20		25	
1Ø Horsepower	1		1		1		2		3	
120V	1		1		1		2		3	
240V	2		2		1		3		5	
Dimension - mm (inches)	63 (2-31/64) - Height 90 (3-35/64) - Width 76 (3) - Depth ②		63 (2-31/64) - Height 90 (3-35/64) - Width 85 (3-11/32) - Depth ②		72 (2-55/64) - Height 108 (4-1/4) - Width 99 (3-57/64) - Depth ②					

Changeover (Center OFF) 6 Pole 	 Metal		 Metal	
	Catalog Number	Price	Catalog Number	Price
Changeover >	LE7-80-3753	305.08	LE7-100-3753	398.55
6 Pole >	LE7-80-1756	333.84	LE7-100-1756	437.58
Amp Rating (encl.)				
UL/CSA	80		100	
IEC/VDE/BS	80		100	
3Ø Horsepower				
240V	25		30	
480V	40		50	
600V	50		50	
1Ø Horsepower				
120V	5		7.5	
240V	10		15	
Dimension - mm (inches)	90 (3-35/64) - Height 144 (5-43/64) - Width 115 (4-17/32) - Depth ②			

- ① 3 Pole Changeover Switch has center OFF — 1 — 2
- ② Dimension without shaft.

Base Mounted 3 Pole Switches - 90° Throw ①③

3 Pole 	 Plastic		 Plastic		 Metal					
	Catalog Number	Price	Catalog Num.	Price	Catalog Num.	Price	Catalog Num.	Price	Catalog Num.	Price
3 Pole >	LA7-16-1753	68.83	LA7-25-1753	82.17	LA7-32-1753	89.37	LA7-40-1753	105.80	LA7-63-1753	132.51
Amp Rating (encl.)										
UL/CSA	16		25		32		40		63	
IEC/VDE/BS	16		25		32		40		63	
3Ø Horsepower										
240V	3		5		7.5		10		15	
480V	7.5		10		15		20		25	
600V	10		10		15		20		25	
1Ø Horsepower										
120V	1		1		1		2		3	
240V	2		2		3		3		5	
Dimension - mm (inches)	63 (2-31/64) - Height 36 (1-27/64) - Width 51 (2-1/64) - Depth ②		63 (2-31/64) - Height 45 (1-49/64) - Width 60 (2-23/64) - Depth ②				72 (2-55/64) - Height 54 (2-1/8) - Width 74 (2-29/32) - Depth ②			

				
	Catalog Num.	Price	Catalog Num.	Price
3 Pole >	LA7-80-1753	191.06	LA7-100-1753	233.17
Amp Rating (encl.)	80		100	
UL/CSA	80		100	
IEC/VDE/BS	80		100	
3Ø Horsepower	25		30	
240V	25		30	
480V	40		50	
600V	50		50	
1Ø Horsepower	5		7.5	
120V	5		7.5	
240V	10		15	
Dimension - mm (inches)	90 (3-35/64) - Height 72 (2-27/32) - Width 90 (3-35/64) - Depth ②			

① Fourth pole side-mounted module available. See page L10.

② Dimension without shaft.

③ Switch Handle position



Base Mounted 3 Pole Changeover and 6 Pole Switches - 90° Throw ①③

Changeover (Center OFF) 6 Pole 	 Metal		 Metal		 Metal					
	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price	Catalog Number	Price
Changeover >	LA7-16-3753	110.94	LA7-25-3753	141.75	LA7-32-3753	162.29	LA7-40-3753	205.44	LA7-63-3753	257.83
6 Pole >	LA7-16-1756	136.62	LA7-25-1756	164.35	LA7-32-1756	183.87	LA7-40-1756	213.65	LA7-63-1756	269.12
Amp Rating (encl.)										
UL/CSA	16		25		32		40		63	
IEC/VDE/BS	16		25		32		40		63	
3Ø Horsepower										
240V	3		5		7.5		10		15	
480V	7.5		10		15		20		25	
600V	10		10		15		20		25	
1Ø Horsepower										
120V	1		1		1		2		3	
240V	2		2		3		3		5	
Dimension - mm (inches)	63 (2-31/64) - Height 90 (3-35/64) - Width 85 (3-11/32) - Depth ②		63 (2-31/64) - Height 90 (3-35/64) - Width 89 (3-1/2) - Depth ②				72 (2-55/64) - Height 108 (4-1/4) - Width 103 (4-1/16) - Depth ②			

Changeover (Center OFF) 6 Pole 	 Metal			
	Catalog Num.	Price	Catalog Num.	Price
Changeover >	LA7-80-3753	343.08	LA7-100-3753	426.28
6 Pole >	LA7-80-1756	381.09	LA7-100-1756	470.45
Amp Rating (encl.)				
UL/CSA	80		100	
IEC/VDE/BS	80		100	
3Ø Horsepower				
240V	25		30	
480V	40		50	
600V	50		50	
1Ø Horsepower				
120V	5		7.5	
240V	10		15	
Dimension - mm (inches)	90 (3-35/64) - Height 144 (5-43/64) - Width 119 (4-17/32) - Depth ②			

① 3 Pole Changeover Switch has center OFF — 1 — 2

② Dimension without shaft.

③ Insert LA2-G3399 is required for 3-position changeover switches when using LA2-G339_ metal shaft extensions.

Switch Handle Assemblies (LA and LE Switches)

Switch Handle Assembly ❶	Color	Mounting Method	Protection Rating	For use with...	Frame Size	Legend ❷	Catalog Number	Price
 Type A	Silver Legend ❷ Black Knob	Screw Fixing ❶	Type 12, IP66	LA/LE7-16...63A	48 X 48	0-I OFF-ON 1-0-2 ❸	LFS2-A-4-175 LFS2-A-4-175I LFS2-A-4-375	9.79
			Type 12, IP66	LA/LE7-25...100A ❹	64 X 64	0-I OFF-ON 1-0-2 ❸	LFS2-A-6-175 LFS2-A-6-175I LFS2-A-6-375	12.90
			Type 12, IP66	LA/LE7-40...100A	88 X 88	0-I OFF-ON 1-0-2 ❸	LFS2-A-8-175 ❺ LFS2-A-8-175I ❺ LFS2-A-8-375	37.80
		Central Nut	Type 12, IP66	LE7-16...63A	48 X 48	0-I OFF-ON	LFC2-A-4-175 LFC2-A-4-175I	13.60
 Type E	Silver Legend ❷ Black Knob ❸	Screw Fixing ❶	Type 12, IP66	LA/LE7-16...63A	48 X 48	0-I OFF-ON 1-0-2 ❸	LFS2-E-4-175 LFS2-E-4-175I LFS2-E-4-375	14.70
			Type 12, IP66	LA/LE7-25...100A ❹	64 X 64	0-I OFF-ON 1-0-2 ❸	LFS2-E-6-175 LFS2-E-6-175I LFS2-E-6-375	18.20
		Central Nut	Type 12, IP66	LE7-16...63A	48 X 48	0-I OFF-ON	LFC2-E-4-175 LFC2-E-4-175I	15.60
 Type I	Yellow Legend ❷ Red Knob	Screw Fixing ❶	Type 12, IP66	LA/LE7-16...63A	48 X 48	0-I OFF-ON 1-0-2 ❸	LFS2-I-4-175 LFS2-I-4-175I LFS2-I-4-375	9.79
			Type 12, IP66	LA/LE7-25...100A ❹	64 X 64	0-I OFF-ON 1-0-2 ❸	LFS2-I-6-175 LFS2-I-6-175I LFS2-I-6-375	12.90
			Type 12, IP66	LA/LE7-40...100A	88 X 88	0-I OFF-ON 1-0-2 ❸	LFS2-I-8-175 ❺ LFS2-I-8-175I ❺ LFS2-I-8-375	37.80
		Central Nut	Type 12, IP66	LE7-16...63A	48 X 48	0-I OFF-ON	LFC2-I-4-175 LFC2-I-4-175I	15.60
 Type L	Yellow Legend ❷ Red Knob ❸	Screw Fixing ❶	Type 12, IP66	LA/LE7-16...63A	48 X 48	0-I OFF-ON 1-0-2 ❸	LFS2-L-4-175 LFS2-L-4-175I LFS2-L-4-375	14.70
			Type 12, IP66	LA/LE7-25...100A ❹	64 X 64	0-I OFF-ON	LFS2-L-6-175 LFS2-L-6-175I	18.00
		Central Nut	Type 12, IP66	LE7-16...63A	48 X 48	0-I OFF-ON	LFC2-L-4-175 LFC2-L-4-175I	15.60

❶ Mounting screws included with Switch Body Assembly.

❷ For blank legend plate, substitute "000" for last three digits in catalog number.
Example: LFS2-A-4-000.

❸ Lockable in OFF position, ON position or both.

❹ Only for use with 3 Pole Changeover switch.

❺ Only for use with LA/LE7-25...63 three pole Changeover Switches. Use 88 x 88 Switch Handle for 80 and 100A Changeover Switch.

❻ This handle cannot be used on a mechanical coupling accessory L2-G3* when coupling any LE7 switches. Must select smaller 48x48 or 64x64 type handles for LE7 coupling applications.

Switch Handle Assemblies (LA and LE Switches)

Switch Handle Assembly ❶	Color	Mounting Method	Protection Rating	For use with...	Frame Size	Legend ❷	Catalog Number	Price
 Type G	Gray Frame Black Handle ❷	Screw Fixing ❶	Type 12, IP66	LA/LE7-16	54 x 54	0 — I OFF — ON	LFS7-G-4-175	14.30
			Type 12, IP66	LA7-16...100A LE7-25...100A	67 x 67	0 — I OFF — ON	LFS2-G-6-175	24.20
			Type 12, IP66	LA/LE7-40...100A	90 x 90	0 — I OFF — ON	LFS2-G-8-175 ❸	44.30
		Central Nut	Type 12, IP66	LE7-16...63A	67 x 67	0 — I OFF — ON	LFC2-G-6-175	27.30
 Type N	Yellow Frame Red Handle ❷	Screw Fixing ❶	Type 12, IP66	LA/LE7-16	54 x 54	0 — I OFF — ON	LFS7-N-4-175	14.30
			Type 12, IP66	LA7-16...100A LE7-25...100A	67 x 67	0 — I OFF — ON	LFS2-N-6-175	24.20
			Type 12, IP66	LA/LE7-40...100A	90 x 90	0 — I OFF — ON	LFS2-N-8-175 ❸	44.30
		Central Nut	Type 12, IP66	LE7-16...63A	67x67	0 — I OFF — ON	LFC2-N-6-175	27.30

Switch Handle Assemblies for LA7 Switches - Type 4/4X ❸

Switch Handle Assembly	Mounting Method	Protection Rating	For use with...	Frame Size	Legend ❷	Color	Catalog Number	Price
 Type R	Screw Fixing Configurable for defeatable or non-defeatable ❹❺	Type 3R, 3, 12, 4, 4X IP66	LA7-16...100A	48.7 x 47	0 — I OFF — ON	Black Frame Black Handle	LA7-SB	45.40
		Type 3R, 3, 12, 4, 4X IP66		48.7 x 47	0 — I OFF — ON	Yellow Frame Red Handle	LA7-SY	45.40
 Type R ❶	Screw Fixing Configurable for defeatable or non-defeatable ❶❹❺	Type 3R, 3, 12, 4, 4X	LA7-16...100A	80 x 114	0 — I OFF — ON	Black Frame Black Handle	L11-PB	See page L30
		Type 3R, 3, 12, 4, 4X		80 x 114	0 — I OFF — ON	Yellow Frame Red Handle	L11-PY	See page L30

❶ Mounting screws included with Switch Body Assembly.

❷ Lockable in OFF position with up to 3 padlocks.

❸ For LA7 base mount switches only.

❹ Switch handle can be field modified to be defeatable or non-defeatable.

❺ Handles LA7-S_ and L11-P_ require R-type Switch Handle Shaft Extension. See page L13.

❻ This handle cannot be used on a mechanical coupling accessory L2-G3* when coupling any LE7 switches. Must select smaller 48x48 or 64x64 type handles for LE7 coupling applications.


Auxiliary Contact Blocks ②

Aux. Contact Block	Contact Configuration	For use with...	Catalog Number	Price
One NO (Early Break) ①				
		LE7-16	LE7-16-P-D10	43.40
		LE7-25...100	LE7-P-D10	43.40
		LA7-16	LA7-16-P-D10	43.40
		LA7-25...100	LA7-P-D10	43.40
One NO and One NC (Instantaneous)				
		LE7-16...100	LE7-P-11	43.40
		LA7-16...100	LA7-P-11	43.40
One NOEM and One NCLB (Make Before Break)				
		LE7-16...100	LE7-PL-11	43.40
		LA7-16...100	LA7-PL-11	43.40
Two NO and Two NC (Instantaneous)				
		LE7-16...100	LE7-P-22	86.90
		LA7-16...100	LA7-P-22	86.90

Fourth Pole ②



Fourth Pole	Contact Configuration	For use with...	Catalog Number	Price
Early Make-Late Break				
		LE7-16	LE7-16-NP	27.00
		LE7-25	LE7-25-NP	29.90
		LE7-32	LE7-32-NP	37.00
		LE7-40	LE7-40-NP	41.00
		LE7-63	LE7-63-NP	49.30
		LE7-80	LE7-80-NP	57.50
		LE7-100	LE7-100-NP	72.70
		LA7-16	LA7-16-NP	27.00
		LA7-25	LA7-25-NP	29.90
		LA7-32	LA7-32-NP	37.00
		LA7-40	LA7-40-NP	41.00
		LA7-63	LA7-63-NP	49.30
		LA7-80	LA7-80-NP	57.50
		LA7-100	LA7-100-NP	72.70

Ground & Neutral Terminals ②

Terminal	Contact Configuration	For use with...	Catalog Number	Price
Ground Terminal				
		LA7-16	LA7-16-PE	22.20
		LA7-25 & 32	LA7-32-PE	22.50
		LA7-40 & 63	LA7-63-PE	29.90
		LA7-80 & 100	LA7-100-PE	45.20
		LE7-16	LE7-16-PE	22.20
		LE7-25 & 32	LE7-32-PE	22.20
		LE7-40 & 63	LE7-63-PE	29.70
		LE7-80 & 100	LE7-100-PE	43.40
		LA7-16	LA7-16-TN	22.20
		LA7-25 & 32	LA7-32-TN	22.50
		LA7-40 & 63	LA7-63-TN	29.90
		LA7-80 & 100	LA7-100-TN	45.20
		LE7-16	LE7-16-TN	22.20
		LE7-20 & 32	LE7-32-TN	22.20
		LE7-40 & 63	LE7-63-TN	49.30
		LE7-80 & 100	LE7-100-TN	43.40



Accessory Mounting Guide

Various accessories can be mounted simultaneously on both the LA7 (base mount) and LE7 (front mount) switch bodies. The drawings below illustrate which combinations are possible.



- ① All N.O. Early Break Contact Blocks mount on the left and/or right side by themselves, or with -NP, -PE, -TN aux on the opposite side. Stacking additional aux contacts on these blocks is not possible.
- ② A maximum of two side-mount accessories may be added to an L7 switch (one on each side)

L7 Switch Accessories

Accessory	Description	Catalog Number	Price Each	
 (Reducer included)	End Shaft - for LE switch ② - Replacement 44mm shaft supplied standard with all switches Sold only in packages of 5. Order 5 pieces to receive 1 pkg of 5.	Plastic Metal	L2-G3380 L7-G3688 ①	5.26 10.60
	Terminal cover - 3 pole LE/LA7-16 LE/LA7-25/32 LE/LA7-40/63 LE/LA7-80/100	L7-16-C3 L7-25-C3 L7-40-C3 L7-80-C3	7.75 8.83 10.60 14.50	
	Terminal cover - 4 pole LE/LA7-25/32 LE/LA7-40/63 LE/LA7-80/100	L7-25-C4 L7-40-C4 L7-80-C4	10.60 13.80 18.80	
	6 Pole Mechanical Coupling - ②③ joins two L7 switches (front or base mount) to form a 6 pole switch (includes 44 mm metal End Shafts for both LE and LA switch) LE7-16 LE/LA7-25 & 32 LE/LA7-40 & 63 LE/LA7-80 & 100	L7-G3821 L7-G3660 L7-G3661 L7-G3662	32.90 41.30 48.20 50.80	
	Snap-on Nameplate & Holder Snaps on to switch handle frames of the following sizes: For 48x48, 64x64 & 67x67	L2-G3667	5.78	
	Nameplate for Snap-on Holder fits cat. # L2-G3667 & L2-G3515 For L2-G3667 “Main Switch” “Emergency Off” For L2-G3515 “Main Switch” “Emergency Off”	L2-G3667A L2-G3667H L2-G3515A L2-G3515H	5.78 5.78 10.10 10.10	
	Handle Assembly Wrench Used for tightening LA7-S-_ handles during assembly	LA7-N245	45.40	

① LE7-40...100 3-pole switches and LE7-16...100 6-pole/Changeover switches come standard with a 44mm **metal** End Shaft. LE7-16...32 3-pole switches come standard with a 44mm **plastic** End Shaft.


② When using mechanical coupler to join two LE7 or LA7 three pole switches, terminal markings will be:

To obtain terminal markings $\begin{matrix} 1 & 3 & 5 & 7 & 9 & 11 \\ \downarrow & \downarrow & \downarrow & \downarrow & \downarrow & \downarrow \\ 2 & 4 & 6 & 8 & 10 & 12 \end{matrix}$ order six pole switch from pages L5 and L7. Coupling for changeover switch is not available.

③ Mechanical couplings applied to all LE7 front mount switches must use LFS2- 48x48 or 64x64 type handles. 6-Pole Mechanical Couplings are not designed for use with LFS2- 88x88 or 90x90 type handles. Mechanical couplings applied to all LA7 base mount switches may use all types of LFS2 handles where applicable.

Modular shaft extension system

Shaft Extension Modules are ideal for lengthening the shaft of an LA7 switch up to 144mm (≈5.5"). These rugged polycarbonate modules are 24mm (≈15/16") long and snap on "piggyback" to one another without the use of tools. Strong center shafts interlock as each module is snapped together. The standard 44mm End Shaft supplied with every LA7 switch connects the last Extension Module with the Switch Handle Assembly. End Shafts of 52 and 57mm are also available, making this modular system versatile, fast and economical. Shaft Extension Modules are supplied two per package.




Modular Shaft Extension Components ③

Component	Description	Catalog Number	Price
	44mm End Shaft - one 44mm shaft supplied standard with all switches		
	Plastic shaft	LA2-G2830	4.02
	Metal shaft	L7-G3687 ②	8.02
	52mm End Shaft -		
	Plastic shaft	LA2-G3194	4.63
	Metal shaft	L7-G3707 ②	9.22
	57mm End Shaft -		
	Plastic shaft	LA2-G3195	5.26
	Extension Modules - Two per package (priced per package)	LA2-G2853	8.37

Determining modular shaft extension components

- Determine Mounting Depth. This is the distance from the inside mounting surface of the enclosure to the **outside surface** of the enclosure cover. See diagram below for details. ①



- If necessary convert Mounting Depth inches to millimeters (inches x 25.4 = millimeters).

NOTE: Table is based on a standard 3 or 4 pole switch body. For 6 pole switches, **deduct 25mm** from the overall Mounting Depth before referring to table.

- In the Modular Shaft Extension Table to the right, find the Mounting Depth in the column under the appropriate LA7 Switch Body.
- Order the End Shaft and number of Extension Modules required for that Mounting Depth.

Modular Shaft Extension Table

Number of Extension Modules	Required End Shaft	Mounting Depth (mm) ①			
		Switch Body LA7-16	Switch Body LA7-25/32	Switch Body LA7-40/63	Switch Body LA7-80/100
0	44mm ②	57.5-63.5	66.5-72.5	79.5-84.5	96-102
0	52mm	65-73	74-82	81.5-94	98-111.5
0	57mm	70-78	79-87	86.5-99	103-116.5
1	44mm ②	81.5-87.5	90.5-96.5	103.5-109.5	120-126
1	52mm	83.5-97	92.5-106	105.5-119	122-135.5
1	57mm	88.5-102	97.5-111	110.5-124	127-140.5
2	44mm ②	105.5-111.5	114.5-120.5	127.5-133.5	144-150
2	52mm	107.5-121	116.5-130	129.5-143	146-159.5
2	57mm	112.5-126	121.5-135	134.5-148	151-164.5
3	44mm ②	129.5-135.5	138.5-144.5	151.5-157.5	168-174
3	52mm	131.5-145	140.5-154	153.5-167	170-183.5
3	57mm	136.5-150	145.5-159	158.5-172	175-188.5
4	44mm ②	153.5-159.5	162.5-168.5	175.5-181.5	192-198
4	52mm	155.5-169	164.5-178	177.5-191	194-207.5
4	57mm	160.5-174	169.5-183	182.5-196	199-212.5
5	44mm ②	177.5-183.5	186.5-192.5	199.5-205.5	216-222
5	52mm	179.5-193	188.5-202	201.5-215	218-231.5
5	57mm	184.5-198	193.5-207	206.5-220	223-236.5
6	44mm ②	201.5-207.5	210.5-216.5	223.5-229.5	240-246
6	52mm	203.5-217	212.5-226	225.5-239	242-255.5
6	57mm	208.5-222	217.5-231	230.5-244	247-260.5

① For DIN rail mounted devices, remember to deduct the offset distance provided by the rail. For example, deduct 2.5mm from the Mounting Depth for switch bodies mounted on DIN 46277 rail.

② LA7-40...100 3-pole switches and LA7-16...100 6-pole/Changeover switches come standard with a 44mm **metal** End Shaft. LA7-16...32 3-pole switches come standard with a 44mm **plastic** End Shaft.

③ Order replacement End Shafts for LE (front mount switches) from page L11.

L7 Enclosed Motor Disconnects (UL and CSA Approved Enclosures) ①⑤

Amp/Horsepower Rating						Painted Steel -UL Type 1/3/12/4 LFS2 Operator - Type 12/IP66 ⑦			Nonmetallic - UL Type 1/3/12/4 LFS2 Operator - Type 12/IP66 ⑦			Nonmetallic - UL Type 4/4X Operator - UL Type 4/4X			Stainless Steel - UL Type 4/4X Operator - UL Type 4/4X		
												 LA7-S handle shown			 L11-P handle shown		
UL/ CSA Amps	Horsepower					Catalog Number	Price	Dimension ③	Catalog Number	Price	Dimension ③	Catalog Number	Price	Dimension ③	Catalog Number	Price	Dimension ③
	1Ø		3Ø														
	120V	240V	240V	480V	600V												
3 Pole - ON/OFF																	
16	1	2	3	7.5	10	LA7-16-1753-WN	219	A	LA7-16-1753-CN	249	C	LA7-16-1753-CR	258	C	LA7-16-1753-SR	830	A
25	1	2	5	10	10	LA7-25-1753-WN	246	A	LA7-25-1753-CN	264	C	LA7-25-1753-CR	287	C	LA7-25-1753-SR	883	A
32	1	3	7.5	15	15	LA7-32-1753-WN	264	A	LA7-32-1753-CN	280	C	LA7-32-1753-CR	314	C	LA7-32-1753-SR	914	A
40	2	3	10	20	20	LA7-40-1753-WN	280	A	LA7-40-1753-CN	306	C	LA7-40-1753-CR	394	C	LA7-40-1753-SR	950	A
63	3	5	15	25	25	LA7-63-1753-WN	311	A	LA7-63-1753-CN	333	C	LA7-63-1753-CR	425	C	LA7-63-1753-SR	969	A
80	5	10	25	40	50	LA7-80-1753-WN	345	B	LA7-80-1753-CN	482	D	LA7-80-1753-CR	466	D	LA7-80-1753-SR	1003	B
100	7.5	15	30	50	50	LA7-100-1753-WN	392	B	LA7-100-1753-CN	526	D	LA7-100-1753-CR	504	D	LA7-100-1753-SR	1053	B
4 Pole - ON/OFF ④																	
16	1	2	3	7.5	10	LA7-16-1754-WN	240	A	LA7-16-1754-CN	272	C	LA7-16-1754-CR	325	C	LA7-16-1754-SR	868	A
25	1	2	5	10	10	LA7-25-1754-WN	264	A	LA7-25-1754-CN	294	C	LA7-25-1754-CR	347	C	LA7-25-1754-SR	889	A
32	1	3	7.5	15	15	LA7-32-1754-WN	282	A	LA7-32-1754-CN	315	C	LA7-32-1754-CR	367	C	LA7-32-1754-SR	910	A
40	2	3	10	20	20	LA7-40-1754-WN	323	A	LA7-40-1754-CN	347	C	LA7-40-1754-CR	401	C	LA7-40-1754-SR	942	A
63	3	5	15	25	25	LA7-63-1754-WN	350	A	LA7-63-1754-CN	381	C	LA7-63-1754-CR	436	C	LA7-63-1754-SR	978	A
80	5	10	25	40	50	LA7-80-1754-WN	393	B	LA7-80-1754-CN	535	D	LA7-80-1754-CR	621	D	LA7-80-1754-SR	1392	B
100	7.5	15	30	50	50	LA7-100-1754-WN	453	B	LA7-100-1754-CN	595	D	LA7-100-1754-CR	658	D	LA7-100-1754-SR	1453	B
6 Pole - ON/OFF																	
16	1	2	3	7.5	10	LA7-16-1756-WN	271	B	LA7-16-1756-CN	423	D	LA7-16-1756-CR	442	D	LA7-16-1756-SR	1335	B
25	1	2	5	10	10	LA7-25-1756-WN	306	B	LA7-25-1756-CN	453	D	LA7-25-1756-CR	601	D	LA7-25-1756-SR	1374	B
32	1	3	7.5	15	15	LA7-32-1756-WN	340	B	LA7-32-1756-CN	484	D	LA7-32-1756-CR	756	D	LA7-32-1756-SR	1420	B
40	2	3	10	20	20	LA7-40-1756-WN	397	B	LA7-40-1756-CN	539	D	LA7-40-1756-CR	592	D	LA7-40-1756-SR	1464	B
63	3	5	15	25	25	LA7-63-1756-WN	445	B	LA7-63-1756-CN	587	D	LA7-63-1756-CR	959	D	LA7-63-1756-SR	1526	B

Modifications (Factory Assembled) ②

Description	Catalog Number Suffix	Adder
Ground Terminal		
For LA7-16	-PE	22.20
For LA7-25 & 32	-PE	22.50
For LA7-40 & 63	-PE	29.90
For LA7-80 & 100	-PE	45.20
Neutral Terminal		
For LA7-16	-TN ③	22.20
For LA7-25 & 32	-TN ③	22.50
For LA7-40 & 63	-TN ③	29.90
For LA7-80 & 100	-TN ③	45.20

NOTE: All -WN and -CN Enclosed Disconnects come standard with a round, yellow and red, screw fixing handle (Type N) with ON/OFF marking. For a round gray and black handle, change "N" to "G". Example: change LA7-25-1753-WN to LA7-25-1753-WG. For a gray and black square handle (LFS2-A), change "N" to "A". For example, change LA7-25-1753-WN to LA7-25-1753-WA.

All -CR and -SR Enclosed Disconnects come standard with a round yellow and red handle set to defeatable door interlocking mode (Type R) and ON/OFF marking. For a black handle change "R" to "B". For example, change LA7-25-1753-CR to LA7-25-1753-CB. *Note: L11-S*/P* Handles can be field converted to non-defeatable mode by inserting a plastic tab which ships in a packet with the enclosed assemblies. See pages L8...L9 for descriptions of all Switch Handle Assemblies.*

① UL/CSA Approved enclosures do not provide for knockouts. Wire opening must be drilled by user.

② Up to two modifications available per Enclosed Disconnect (one modification possible on 4 pole switches).

③ Not available on four pole switches.

④ One additional factory modification possible.

⑤ Non-metallic enclosures are fiberglass reinforced polyester type.

⑥ LA7-...-CR and -SR Enclosures with dim codes A and C include LA7-S_ Handles, and dim codes B and D include L11-P_ handles. Transition to LA7-S* handles will be a gradual change.

⑦ To substitute L11 4X handle add -PY for yellow/red or -PB for black handle; For example: LA7-25-1753-WN changes to LA7-25-1753-WN-PY. Add \$32 to list price.

L7 Enclosed Motor Disconnects (UL and CSA Approved Enclosures) ①

Amp/Horsepower Rating						Painted Steel - UL Type 1/3/12/4 LFS2 Operator - Type 12/IP66 ②			Nonmetallic - UL Type 1/3/12/4 LFS2 Operator - Type 12/IP66 ②			Nonmetallic - UL Type 4/4X Operator - UL Type 4/4X			Stainless Steel - UL Type 4/4X Operator - UL Type 4/4X		
												 LA7-S handle shown			 L11-P handle shown		
UL/CSA Amps	Horsepower					Catalog Number	Price	Dimension ③	Catalog Number	Price	Dimension ③	Catalog Number	Price	Dimension ③			
	1Ø		3Ø														
	120V	240V	240V	480V	600V												
3 Pole - ON/OFF (with 1 NOEM and 1 NCLB - Make Before Break)																	
16	1	2	3	7.5	10	LA7-16-1753-WN-PL11	259	A	LA7-16-1753-CN-PL11	290	C	LA7-16-1753-CR-PL11	305	C	LA7-16-1753-SR-PL11	877	A
25	1	2	5	10	10	LA7-25-1753-WN-PL11	274	A	LA7-25-1753-CN-PL11	306	C	LA7-25-1753-CR-PL11	337	C	LA7-25-1753-SR-PL11	900	A
32	1	3	7.5	15	15	LA7-32-1753-WN-PL11	290	A	LA7-32-1753-CN-PL11	321	C	LA7-32-1753-CR-PL11	365	C	LA7-32-1753-SR-PL11	965	A
40	2	3	10	20	20	LA7-40-1753-WN-PL11	319	A	LA7-40-1753-CN-PL11	352	C	LA7-40-1753-CR-PL11	404	C	LA7-40-1753-SR-PL11	947	A
63	3	5	15	25	25	LA7-63-1753-WN-PL11	347	A	LA7-63-1753-CN-PL11	379	C	LA7-63-1753-CR-PL11	476	C	LA7-63-1753-SR-PL11	1020	A
80	5	10	25	40	50	LA7-80-1753-WN-PL11	391	B	LA7-80-1753-CN-PL11	533	D	LA7-80-1753-CR-PL11	517	D	LA7-80-1753-SR-PL11	1389	B
100	7.5	15	30	50	50	LA7-100-1753-WN-PL11	433	B	LA7-100-1753-CN-PL11	575	D	LA7-100-1753-CR-PL11	636	D	LA7-100-1753-SR-PL11	1104	B
4 Pole - ON/OFF (with 1 NOEM and 1 NCLB - Make Before Break) ③																	
16	1	2	3	7.5	10	LA7-16-1754-WN-PL11	280	A	LA7-16-1754-CN-PL11	232	C	LA7-16-1754-CR-PL11	284	C	LA7-16-1754-SR-PL11	827	A
25	1	2	5	10	10	LA7-25-1754-WN-PL11	301	A	LA7-25-1754-CN-PL11	294	C	LA7-25-1754-CR-PL11	347	C	LA7-25-1754-SR-PL11	889	A
32	1	3	7.5	15	15	LA7-32-1754-WN-PL11	323	A	LA7-32-1754-CN-PL11	356	C	LA7-32-1754-CR-PL11	409	C	LA7-32-1754-SR-PL11	951	A
40	2	3	10	20	20	LA7-40-1754-WN-PL11	370	A	LA7-40-1754-CN-PL11	393	C	LA7-40-1754-CR-PL11	445	C	LA7-40-1754-SR-PL11	988	A
63	3	5	15	25	25	LA7-63-1754-WN-PL11	397	A	LA7-63-1754-CN-PL11	428	C	LA7-63-1754-CR-PL11	480	C	LA7-63-1754-SR-PL11	1023	A
80	5	10	25	40	50	LA7-80-1754-WN-PL11	443	B	LA7-80-1754-CN-PL11	585	D	LA7-80-1754-CR-PL11	646	D	LA7-80-1754-SR-PL11	1441	B
100	7.5	15	30	50	50	LA7-100-1754-WN-PL11	504	B	LA7-100-1754-CN-PL11	646	D	LA7-100-1754-CR-PL11	706	D	LA7-100-1754-SR-PL11	1502	B
6 Pole - ON/OFF (with 1 NOEM and 1 NCLB - Make Before Break)																	
16	1	2	3	7.5	10	LA7-16-1756-WN-PL11	319	B	LA7-16-1756-CN-PL11	461	D	LA7-16-1756-CR-PL11	516	D	LA7-16-1756-SR-PL11	1311	B
25	1	2	5	10	10	LA7-25-1756-WN-PL11	350	B	LA7-25-1756-CN-PL11	492	D	LA7-25-1756-CR-PL11	546	D	LA7-25-1756-SR-PL11	1343	B
32	1	3	7.5	15	15	LA7-32-1756-WN-PL11	381	B	LA7-32-1756-CN-PL11	523	D	LA7-32-1756-CR-PL11	578	D	LA7-32-1756-SR-PL11	1373	B
40	2	3	10	20	20	LA7-40-1756-WN-PL11	443	B	LA7-40-1756-CN-PL11	585	D	LA7-40-1756-CR-PL11	638	D	LA7-40-1756-SR-PL11	1434	B
63	3	5	15	25	25	LA7-63-1756-WN-PL11	490	B	LA7-63-1756-CN-PL11	632	D	LA7-63-1756-CR-PL11	687	D	LA7-63-1756-SR-PL11	1482	B

Modifications (Factory Assembled) ②

Description	Catalog Number Suffix	Adder
Ground Terminal		
For LA7-16	-PE	22.20
For LA7-25 & 32	-PE	22.50
For LA7-40 & 63	-PE	29.90
For LA7-80 & 100	-PE	45.20
Neutral Terminal		
For LA7-16	-TN	22.20
For LA7-25 & 32	-TN	22.50
For LA7-40 & 63	-TN	29.90
For LA7-80 & 100	-TN	45.20

NOTE: All -WN and -CN Enclosed Disconnects come standard with a round, yellow and red, screw fixing handle (Type N) with ON/OFF marking. For a round gray and black handle, change "N" to "G". Example: change LA7-25-1753-WN to LA7-25-1753-WG. For a gray and black square handle (Type A), change "N" to "A". Example: change LA7-25-1753-WN to LA7-25-1753-WA.

All -CR and -SR Enclosed Disconnects come standard with a round yellow and red handle set to defeatable door interlocking mode (Type R) and ON/OFF marking. For a black handle change "R" to "B". For example, change LA7-25-1754-CR-PL11 to LA7-25-1754-CB-PL11. *Note: L11-S*/P* Handles can be field converted to non-defeatable mode by inserting a plastic tab which ships in a packet with the enclosed assemblies. See pages L8...L9 for descriptions of all Switch Handle Assemblies.*



- ① UL/CSA Approved enclosures do not provide for knockouts. Wire opening must be drilled by user.
- ② One modification available per Enclosed Disconnect (no modifications available on 4 pole).
- ③ Factory modifications not available.
- ④ Nonmetallic enclosures are fiberglass reinforced polyester type.

- ⑤ LA7-...-CR and -SR Enclosures with dim codes A & C include LA7-S_ Handles, and dim codes B & D include L11-P_ handles. Transition to LA7-S* handles will be a gradual change.
- ⑥ To substitute L11 4X handle add -PY for yellow/red or -PB for black handle. For example: LA7-25-1753-WN-PL11 changes to LA7-25-1753-WN-PY-PL11. Add \$32 to list price.

LY7 Enclosed Load Disconnect Switches (IP Rated Enclosures) ①

Amp/Horsepower Rating						Plastic - IP66 ABS Enclosure Operator - IP66, Red/Yellow (Type N)		Plastic - IP66 ABS Enclosure Operator - IP66, Gray/Black (Type G)		Plastic - IP66 ABS Enclosure Operator - IP66, Silver/Black (Type A)	
											
UL/ CSA Amps	Horsepower					Catalog Number	Price	Catalog Number	Price	Catalog Number	Price
	1Ø		3Ø								
	120V	240V	240V	480V	600V						
3 Pole - ON/OFF											
16	1	2	3	7.5	10	LY7-16M-1753-N4	99.64	LY7-16M-1753-G4	99.64	LY7-16M-1753-A4	98.61
25	1	2	5	10	10	LY7-25-1753-N6	158.19	LY7-25-1753-G6	158.19	LY7-25-1753-A6	145.86
32	1	3	7.5	15	15	LY7-32-1753-N6	163.33	LY7-32-1753-G6	163.33	LY7-32-1753-A6	149.97
40	2	3	10	20	20	LY7-40-1753-N6	207.49	LY7-40-1753-G6	207.49	LY7-40-1753-A6	197.22
63	3	5	15	25	25	LY7-63-1753-N6	219.82	LY7-63-1753-G6	219.82	LY7-63-1753-A6	207.49
80	5	10	25	40	50	LY7-80-1753-N6	306.10	LY7-80-1753-G6	306.10	LY7-80-1753-A6	292.75
100	7.5	15	30	50	50	LY7-100-1753-N6	345.13	LY7-100-1753-G6	345.13	LY7-100-1753-A6	332.81
6 Pole - ON/OFF											
16	1	2	3	7.5	10	LY7-16M-1756-N6	200.31	LY7-16M-1756-G6	200.31	LY7-16M-1756-A6	197.22
25	1	2	5	10	10	LY7-25-1756-N6	316.37	LY7-25-1756-G6	316.37	LY7-25-1756-A6	291.72
32	1	3	7.5	15	15	LY7-32-1756-N6	325.62	LY7-32-1756-G6	325.62	LY7-32-1756-A6	303.02
40	2	3	10	20	20	LY7-40-1756-N6	417.04	LY7-40-1756-G6	417.04	LY7-40-1756-A6	404.00
63	3	5	15	25	25	LY7-63-1756-N6	440.67	LY7-63-1756-G6	440.67	LY7-63-1756-A6	414.98

Assembled L7 Disconnect Switches

Switch	Description	Function	Color	Circuit	Poles	UL/CSA Amps	Catalog Number	Price
	Type Q Load Switch - This pre-assembled switch is designed for panels with standard 45mm cutouts. The specially designed switch handle also makes it ideal for mounting <i>within</i> a distribution panel when ready access to the operator is not desired. Finger-proof to IP20.		Gray face/ Black Handle		3	25	LA7-25-1753-Q	108.88
						32	LA7-32-1753-Q	118.13
	Emergency Off Switch - This yellow and red pre-assembled switch is designed as an Emergency Off for panels with standard 45mm cutouts. The specially designed switch handle also makes it ideal for mounting <i>within</i> a distribution panel when a color coded OFF switch is desired. Finger-proof to IP20 with provision for locking with one padlock.		Yellow face/ Red handle		3	25	LA7-25-1753-R	108.88
						32	LA7-32-1753-R	118.13

① Suitable for use in NEMA 4 type applications (not UL listed).

Thermoplastic Enclosures (IP Rated)

Accessory	Description	Enclosure Size	For use with...	Poles	Shaft Required...	Catalog Number	Price
	ABS Enclosure – For High Impact Applications IP66, UL94 Flame Resistance - HB Includes 1 Grounding/Neutral terminal.	95 (W) x 150 (H) x 86 (D)	LA7-25...32	3 / 4	LA2-G3194	LA2-G3572	70.10
		95 (W) x 150 (H) x 111 (D)				LA2-G3573	77.00
	With pre-drilled holes for 64 x 64 operator or larger	125 (W) x 180 (H) x 105 (D)	LA7-25...32	6	With switch Supplied with enclosure	L7-G3663	94.70
			LA7-40...63	3 / 4			
	175 (W) x 230 (H) x 120 (D)		LA7-40...63	6	With switch Supplied with enclosure	L7-G3665	128.00
			LA7-80...100	3 / 4			
	Noryl Enclosure – For Corrosion Prone Applications IP66, UL94 Flame Resistance - V0 Includes 1 Grounding/Neutral terminal.	95 (W) x 150 (H) x 86 (D)	LA7-25...32	3 / 4	LA2-G3194	LA2-G3576	98.20
		95 (W) x 150 (H) x 111 (D)				LA2-G3577	108.00
	With pre-drilled holes for 64 x 64 operator or larger	125 (W) x 180 (H) x 105 (D)	LA7-25...32	6	With switch Supplied with enclosure	L7-G3664	134.00
			LA7-40...63	3 / 4			
	175 (W) x 230 (H) x 120 (D)		LA7-40...63	6	With switch Supplied with enclosure	L7-G3666	180.00
			LA7-80...100	3 / 4			
	Without holes	95 (W) x 150 (H) x 86 (D)				LA2-G3574	69.20
		95 (W) x 150 (H) x 111 (D)				LA2-G3575	76.20
		95 (W) x 150 (H) x 86 (D)				LA2-G3578	96.90
		95 (W) x 150 (H) x 111 (D)				LA2-G3579	108.00

Enclosure Accessories

Accessory	Description	For use with...	Pkg Qty	Catalog Number	Price Each
 L7-G3653	Additional Ground & Neutral Terminals - - Provision for two - One included with enclosures above Sold only in quantities of 5. Order 5 pieces to receive one package of 5.	LA2-G357... L7-G366...	5	L7-G3653 L7-G3673	5.00
 L7-G3673					14.50

Technical Information

				16A	25A	32A	40A	63A	80A	100A	Aux. Cont.	
Performance Data												
Rated operational voltage U_e		UL/CSA	[V]	600	600	600	600	600	600	600	600	
		IEC ❶	[V]	690	690	690	690	690	690	690	690	
Rated insulation voltage U_i		UL/CSA	[V]	600	600	600	600	600	600	600	600	
		IEC	[V]	690	690	690	690	690	690	690	690	
Rated impulse voltage U_{imp}		UL/CSA	[kV]	8	8	8	8	8	8	8	8	
Test voltage U_t		1 minute	[kV]	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	
Lost power, per pole			[W]	0.58	1.0	1.5	1.6	2.4	3.6	5.5	0.4	
Rated Frequency			[Hz]	50/60	50/60	50/60	50/60	50/60	50/60	50/60	50/60	
Conventional free air thermal current I_{th} ❶			[A]	25	40	50	63	75	100	120	12	
Conventional enclosed thermal current I_{th} ❶			[A]	20	32	40	50	63	80	100	10	
Rated Current I_e ❶												
AC-1	Non-inductive or only slightly inductive loads	690V	[A]	16	25	32	40	63	80	100	10	
AC-21A												
Switching of resistive loads with slight overload												
Rated Power P_e												
AC-23A	Occasional switching of 3Ø motors and other highly inductive loads (criterion for selecting main switches)	230V	[kW]	5.5	7.5	7.5	15	18.5	22	30	–	
		400V	[kW]	7.5	11	15	22	30	37	55	–	
		690V	[kW]	7.5	11	15	18.5	22	37	45	–	
AC-3	Squirrel cage motors; starting and stopping of running motors	230V	[kW]	4	5.5	7.5	11	15	18.5	22	–	
		400V	[kW]	5.5	7.5	11	15	18.5	30	37	–	
		690V	[kW]	5.5	7.5	11	15	18.5	30	22	–	
Short circuit current (Type 2 coordination)												
Rated conditional short circuit current		400/415V	[kA]	20	20	15	20	15	30	25	–	
Maximum fuse rating of circuit (type g, G)			[A]	20	25	35	50	63	80	100	–	
Rated short-time current 1cw, 1s			[A]	800	900	900	1300	1300	2500	2500	–	
Rated breaking capacity AC23A (cosφ 0.45)		230V	[A]	156	296	296	484	484	780	780	–	
		400V	[A]	120	256	256	504	504	800	800	–	
		690V	[A]	70	136	136	196	196	376	376	–	
DC switching capacity												
Rated current I_e		1 pole	24/48V	[A]	20	25	32	40	63	80	100	–
			110V	[A]	5	5	6	8	10	16	20	–
220V	[A]		1	1	1	1.5	1.5	3	3	–		
440V	[A]		0.5	0.5	0.5	0.6	0.6	0.7	0.7	–		
DC-21A	For resistive loads, T < 1 ms	2 poles	96V	[A]	20	25	32	40	63	80	100	–
			110V	[A]	20	23	25	32	50	70	80	–
			220V	[A]	5	5	6	8	10	16	20	–
			440V	[A]	1	1	1	1.5	1.5	3	3	–
	For inductive loads, T < 15 ms	2 poles	600V	[A]	0.6	0.6	0.6	0.8	0.8	1	1	–
			110V	[A]	20	25	32	40	63	80	100	–
			220V	[A]	13	13	15	20	28	50	63	–
			440V	[A]	2.2	2.2	2.2	3.6	3.6	6.5	6.5	–
	For inductive loads, T < 15 ms	3 poles	600V	[A]	1.3	1.5	1.5	2	2	3	3	–
Rated power P_e		90V	[kW]	1	1.3	1.5	2.9	4.1	5.1	7.2	–	
DC-23A, DC-3, DC-5	3 poles	110V	[kW]	1	1.1	1.3	2.2	3.3	5.5	7	–	
		220V	[kW]	0.8	0.9	1.1	1.7	2	3.5	4.4	–	
		440V	[kW]	0.6	0.6	0.6	0.9	0.9	1.1	1.1	–	
		600V	[kW]	0.4	0.4	0.4	0.5	0.5	0.9	0.9	–	

① See Conformity to Standards on next page.

Technical Information (continued)

Technical Information (continued)			16A	25A	32A	40A	63A	80A	100A	Aux. Cont.		
UL/CSA Data												
Continuous current			[A]	16	25	32	40	63	80	100	—	
Heavy Pilot Duty			[AC]	A600	A600	A600	—	—	—	—	A600	
Standard Duty			[DC]	—	—	—	—	—	—	—	Q600	
Motor Rating 60Hz	Single phase, 2 poles	120V	[FLA]	16	16	16	24	34	56	80	—	
			[HP]	1	1	1	2	3	5	7.5	—	
		240V	[FLA]	12	12	17	17	28	50	68	—	
			[HP]	2	2	3	3	5	10	15	—	
		480V	[FLA]	8.5	8.5	14	21	26	34	68	—	
			[HP]	3	3	5	7.5	10	15	30	—	
		600V	[FLA]	11.2	11.2	11.2	16	20	27	44	—	
			[HP]	5	5	5	7.5	10	15	25	—	
		Three phase	120V	[FLA]	13.6	13.6	19.2	30.4	40	56	84	—
					[HP]	2	2	3	5	7.5	10	15
			240V	[FLA]	9.6	15.2	22	28	42	68	80	—
					[HP]	3	5	7.5	10	15	25	30
480V	[FLA]		11	14	21	27	34	52	65	—		
			[HP]	7.5	10	15	20	25	40	50	—	
600V	[FLA]		11	11	17	22	27	52	52	—		
			[HP]	10	10	15	20	25	50	50	—	

Short Circuit Ratings

Maximum short circuit prospective fault current, RMS symmetrical, 600 VAC max.

When protected by Class K5 fuses, maximum amperes of rated fuse	[KA]	5	5	5	5	5	5	5	–
	[A]	25	35	35	80	80	125	125	–
When protected by J Class fuses, maximum amperes of rated fuse	[KA]	~	65	65	65	65	65	65	–
	[A]	~	30	30	60	60	100	100	–

Mechanical Data

Mechanical Data			16A	25A...32A	40A...63A	80A...100A	Aux. Cont.
Protection class according to IEC 529							
Motor rating 60 Hz							
Actuators			Type 12 / IP66				
Switch bodies			IP20				
Mechanical life	[millions of operations]		0.2				
Maximum wire gauges							
Terminal size per IEC 947-1			A4	A6	A7	A9	2xA2
Fine strands	1/2	[AWG]	(1)16...10/(2)16...12	(1)14...8/(2)14...10	(1)12...4/(2)12...8	(1)10...1/(2)10...4	18...14
	conductor	[mm²]	(1)1...10/(2)1...4	(1)1.5...16/(2)1.5...6	(1)2.5...25/(2)2.5...16	(1)4...50/(2)4...25	0.75...2.5
Rigid wire	1/2	[AWG]	(1)16...8/(2)16...12	(1)14...8/(2)14...10	(1)12...4/(2)12...8	(1)10...1/(2)10...6	18...14
	conductor	[mm²]	(1)1.5...6/(2)1.5...4	(1)1.5...10/(2)1...6	(1)2.5...16/(2)2.5...10	(1)4...35/(2)4...16	0.5...2.5
Tightening Torque	max.	[lb-in]	12	12	25	50	8
		[Nm]	1.4	1.4	2.8	5.6	1.0
Ambient Temperature	Operation	[°C]	-25...+60 °C (-13...+140 °F)				
	Storage	[°C]	-40...+80 °C (-40...+176 °F)				

Conformity to Standards: ①

IEC 947-1, IEC 947-3 Low voltage switchgear and control gear part 3: Switches, disconnectors, switch-disconnectors and fuse-combination units. CE

UL 508: Industrial Control Equipment

CSA: C22.2 No. 14: Industrial Control Equipment

Approvals: ①

UL Listed (File No. E54612 NLRV)

CSA Certified (LR 13002)

CCC Certified

Meets IEC, VDE and BS standard requirements

IEC/CE Marked (Per EN60947-3)


① LA(E)-16 switches are cUL approved.

LE7 Front Mount (3 Pole) with Screw Fixing Handle

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.

Switch Handle		
Type	P	Q
LFS2-A-4	28	48 x 48
LFS2-E-4	28	48 x 48
LFS2-I-4	28	48 x 48
LFS2-L-4	28	48 x 48
LFS2-S-4	28	48 x 62
LFS2-A-6	28	64 x 64
LFS2-E-6	28	64 x 64
LFS2-I-6	28	64 x 64
LFS2-L-6	28	64 x 64
LFS2-S-6	28	64 x 78
LFS7-G-4	34	54 x 54
LFS7-N-4	34	54 x 54
LFS2-G-6	34	67 x 67
LFS2-N-6	34	67 x 67
LFS2-A-8	45	88 x 88
LFS2-I-8	45	88 x 88
LFS2-G-8	49	88 x 88
LFS2-N-8	49	88 x 88


Switch Body					
Type	B1	B2	F	H	L
LE7-16	—	28	36	63	51
LE7-25/32	—	36	45	63	60
LE7-40/63	48	36	54	72	74
LE7-80/100	48	36	72	90	90



LE7 Front Mount (6 Pole) with Screw Fixing Handle



Switch Handle		
Type	P	Q
LFS2-A-4	28	48 x 48
LFS2-E-4	28	48 x 48
LFS2-I-4	28	48 x 48
LFS2-L-4	28	48 x 48
LFS2-S-4	28	48 x 62
LFS2-A-6	28	64 x 64
LFS2-E-6	28	64 x 64
LFS2-I-6	28	64 x 64
LFS2-L-6	28	64 x 64
LFS2-S-6	28	64 x 78
LFS7-G-4	34	54 x 54
LFS7-N-4	34	54 x 54
LFS2-G-6	34	67 x 67
LFS2-N-6	34	67 x 67
LFS2-A-8	45	88 x 88
LFS2-I-8	45	88 x 88
LFS2-G-8	49	88 x 88
LFS2-N-8	49	88 x 88

Switch Body					
Type	B1	B2	F	H	L
LE7-16	—	28	36	63	51
LE7-25/32	—	36	45	63	60
LE7-40/63	48	36	54	72	74
LE7-80/100	48	36	72	90	90



LE7 Front Mount (3 Pole) with Central Nut Fixing Handle

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Switch Handle

Type	P	Q
LFC2-A-4	29	48 x 48
LFC2-E-4	29	48 x 48
LFC2-I-4	29	48 x 48
LFC2-L-4	29	48 x 48
LFC2-G-6	34	67 x 67
LFC2-N-6	34	67 x 67



Switch Body

Type	L
LE7-16	75.5
LE7-25/32	84.5
LE7-40/63	98.5

LA7 Base Mount (3 Pole) with Screw Fixing Handle

Switch Handle

Type	P	Q	B
LFS2-A-4	28	48 x 48	36
LFS2-E-4	28	48 x 48	36
LFS2-I-4	28	48 x 48	36
LFS2-L-4	28	48 x 48	36
LFS2-S-4	28	48 x 62	36
LFS2-A-6	28	64 x 64	48 (36)
LFS2-E-6	28	64 x 64	48 (36)
LFS2-I-6	28	64 x 64	48 (36)
LFS2-L-6	28	64 x 64	48 (36)
LFS2-S-6	28	64 x 78	48 (36)
LFS7-G-4	34	54 x 54	36
LFS7-N-4	34	54 x 54	36
LFS2-G-6	34	67 x 67	48 (36)
LFS2-N-6	34	67 x 67	48 (36)
LFS2-A-8	45	88 x 88	48
LFS2-I-8	45	88 x 88	48
LFS2-G-8	49	88 x 88	48
LFS2-N-8	49	88 x 88	48



Proximity to Hinge

Type	Y min.	X ≥	Y max.	X ≥
LE7-16	2.5	150	9.5	90
LE7-25/32	2.5	150	9.5	90
LE7-40/63	2.5	150	9.5	90
LE7-80/100	2.5	150	9.5	90

Switch Body

Type	D3	E	F	F3	G	H	L
LA7-16	4.5	70	11	12.5	36	63	55
LA7-25/32	4.5	70	15	15	45	63	59
LA7-40/63	4.5	80	20	17	54	72	73
LA7-80/100	5.6	95	25	23.5	72	90	89

LA7 Base Mount (6 Pole) with Screw Fixing Handle

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.

Switch Handle




Type	P	Q	B
LFS2-A-4	28	48 x 48	36
LFS2-E-4	28	48 x 48	36
LFS2-I-4	28	48 x 48	36
LFS2-L-4	28	48 x 48	36
LFS2-S-4	28	48 x 62	36
LFS2-A-6	28	64 x 64	48 (36)
LFS2-E-6	28	64 x 64	48 (36)
LFS2-I-6	28	64 x 64	48 (36)
LFS2-L-6	28	64 x 64	48 (36)
LFS2-S-6	28	64 x 78	48 (36)
LFS7-G-4	34	54 x 54	36
LFS7-N-4	34	54 x 54	36
LFS2-G-6	34	67 x 67	48 (36)
LFS2-N-6	34	67 x 67	48 (36)
LFS2-A-8	45	88 x 88	48
LFS2-I-8	45	88 x 88	48
LFS2-G-8	49	88 x 88	48
LFS2-N-8	49	88 x 88	48

Proximity to Hinge


Type	Y min.	X ≥	Y max.	X ≥
LE7-16	2.5	150	9.5	90
LE7-25/32	2.5	150	9.5	90
LE7-40/63	2.5	150	9.5	90
LE7-80/100	2.5	150	9.5	90

Switch Body

Type	D3	E	F1	F2	F3	G	H	L
LA7-16	4.5	70	xx	12.5	12.5	90	63	55
LA7-25/32	4.5	70	30	15	15	90	63	84
LA7-40/63	4.5	80	37	17	17	108	72	98
LA7-80/100	5.6	95	48.5	23.5	23.5	144	90	114




Type Q and Emergency Off Switch




Type	P
LA7-25(32)-1753-Q	20
LA7-25(32)-1753-R	23

LA7-SY/SB (Type R) Switch Handle




LA7-SY/SB Assembly




L7 with Auxiliary Contact Blocks


Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Contacts	M
1 N.O. + 1 N.C.	9
2 N.O. + 2 N.C.	18

L7 with Ground, Neutral and Fourth Pole


Type	M
L7-16	12.5
L7-20/32	14
L7-40/63	17.5
L7-80/100	22


Metal Shaft Extension (LA2-G3393[4])


Switch Body	
Type	L
LA7-16	55
LA7-20/32	59
LA7-40/63	73
LA7-80/100	89


Shaft	
Type	A
LA2-G3393	110...235
LA2-G3394	230...350

L7 Enclosed Motor Disconnect


Dimensions are in inches (millimeters). Dimensions not intended for manufacturing purposes.




DIMENSION CODE A



DIMENSION CODE B



DIMENSION CODE C



DIMENSION CODE D

Dimension Code	Handle	Dim X	
		inches	mm
A	LA7-SY/SB	6-9/16	166.8
	LFS2- -6*	6-1/8	155.8
B	L11-PB/PY	7-1/16	180.1
	LFS2- -6*	6-11/16	169.1
C	LA7-SY/SB	6-1/4	158.7
	LFS2- -6*	5-13/16	147.7
D	L11-PB/PY	8	203.7
	LFS2- -6*	7-9/16	192.7

LY7 Enclosed Load Disconnect Switch (and Thermoplastic Enclosures)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.




Figure 1





Figure 2



Enclosure Side View

Type	Figure	Poles	Enclosure		Height A	Width B	Knock Outs		Mounting Holes			Depth H
			ABS	Noryl			ØD1 Ø	ØD2	E	F	G	
LY7-16M	2	3	❶	❶	118	70	16/20	~	50	105	~	70
	2	6	L7-G3663	L7-G3664	180	125	25/30	~	~	~	145	105
LY7-25/32	2	3/4	LA2-G3572	LA2-G3576	150	95	22.5/28.5	22.5	60	115	~	86
	2	6	L7-G3663	L7-G3664	180	125	28.5/37.5	~	~	~	145	105
LY7-40/63	2	3/4	L7-G3663	L7-G3664	180	125	28.5/37.5	~	~	~	145	105
	1	6	L7-G3665	L7-G3666	230	175	37.5/47.5	~	155	195	~	120
LY7-80/100	1	3/4	L7-G3665	L7-G3666	230	175	37.5/47.5	~	155	195	~	120

❶ Empty enclosures not available for purchase

❷ LA7-16 units have one knock-out on each end. All others have two knock-outs on each end.

Notes

Series L11 Fusible up to 800A & Non-fusible Disconnect Switches up to 1200 Amps

Suitable as a UL98
Service Entrance
Disconnecting Means



TIP!



To learn the basic differences between control, load and fusible disconnect switches and how to apply them, see our white paper Tech-LMSD in the online library.

Sprecher + Schuh's L11 series of fused and nonfused disconnect switches complies with UL98 service entrance requirements and is NFPA 79 compliant. This family of rod operated switches is suitable for applications that require small panel space and superior short circuit protection.

Big performance in a small package

L11 disconnects are rated up to 1200A and can be operated at up to 600V. They protect motors up to 500HP (@480V). The L11 may be installed on circuits capable of delivering up to 200,000A of short circuit fault current levels typically found in modern industrial facilities.

The new expanded offering of the L11 disconnect series ranges from 100A through 1200A. The L11 Fusible switches are available from 100A up to 800A, and are designed to be used with Class J & L fuses. The L11 Non-Fusible switches are available from 100A up to 1200A. Optional auxiliary contacts can also be mounted on the switch for control circuit use. The L11 family performance comes in a compact design, leaving room for additional branch circuit components within the panel.

Maximum protection for downstream equipment

L11 switches are UL98 approved as a branch circuit protection device and are engineered to provide excellent short-circuit protection for downstream equipment up to 200kA. The L11 fusible switches accept the latest small dimension Class CC, J, L and HRCII fuses.

This Type 2 protection limits let-through currents to levels specified for IEC equipment, and ensures that when the short circuit is cleared, the device will be operable.




Meets the toughest safety standards

The L11 offers a modular universal internal handle which provides an interlocked handle for test mode use (30A/60A) and UL508A and NFPA 79 compliance in North America. The L11 30A & 60A are equipped with removable fuse carriers which provide dead-front switch protection during fuse change-out. Fuse carriers with neon blown fuse indicators are also available as an option on 30A & 60A models. Test mode D7 auxiliary contacts may be installed to provide test capability of control circuit without energizing the main contacts for the L11-30A/60A switches. The L11 switches meet IP20 for finger-safe wiring terminals and IP30 for touch-safe fuse carriers.

NFPA 79 Compliant

All L11 30/60A & L11 100A...800A Fusible switches are NFPA79 compliant, which meets the following guidelines under the NFPA 79 standards 5.3.3.1 and 6.2.3.1.2.



The supply Circuit Disconnecting Device shall:

- Be provided with a permanent means permitting it to be locked in the open position only independent of the door position.
- Be operable, by qualified persons, independent of the door position without the use of accessory tools or devices.

The interlocking means shall:

- Be reactivated automatically when the door is closed.
- Prevent closing of the disconnecting means while the enclosure door is open, unless an interlock is operated by deliberate action.

International standards and approvals


All Sprecher + Schuh L11 disconnect switches are UL Listed under File Number E47426, CSA, CE Marked and are designed to meet IEC 947-3, and applicable NEMA requirements.

UL/CSA Fused Disconnect Switches ⑤

Switch	Amp Rating (A)	Maximum Horsepower ❶							Catalog Number	Price	Dimension Code
		1 Ø (60Hz)		Three Phase (60Hz)			DC				
		120V	240V	240V	480V	600V	125V	250V			
 30A & 60A Typical  L11-J100A...L800A Typical	UL Class CC and CSA HRCI-Misc Fuses ❷										
	30	2	3	7.5	15	20	3	5	L11-C30-1753	320	A1
	UL Class J and CSA HRCI-J Fuses ❷										
	30	2	3	7.5	15	20	3	5	L11-J30-1753	340	A1
	60	3	10	15	30	50	5	10	L11-J60-1753	435	B1
	100	7.5	15	30	60	75	7.5	20	L11-J100-1753	659	F5
	200	~	25	60	125	150	15	40	L11-J200-1753	1470	F6
	400	~	50	125	250	350	20	50	L11-J400-1753	2780	F7
	600	~	~	200	400	500	~	~	L11-J600-1753	4740	F8
	UL Class L and CSA HRCII-L Fuses										
	800	~	~	200	500	500	~	~	L11-L800-1753	6170	F9
	CSA HRCII-C Fuses										
	30	2	3	7.5	15	20	3	5	L11-H30-1753	336	B1
60	3	10	15	30	50	5	10	L11-H60-1753	427	B1	

Items in Gray available by Special Order only.

UL/CSA Non-Fused Disconnect Switches ③

Switch	④ Amp Rating (A)	Maximum Horsepower							No. of Poles	Catalog Number	Price	Dimension Code
		1 Ø (60Hz)		Three Phase (60Hz)			DC					
		120V	240V	240V	480V	600V	125V	250V				
 30A & 60A Typical  NU100A...1200A Typical	30	2	3	7.5	15	20	3	5	3	L11-N30-1753	295	A2
	60	3	10	15	30	40	5	10	3	L11-N60-1753	389	B2
	100	7.5	15	30	75	100	10	15	3	L11-NU100-1753	659	F1
	200	~	50	75	150	200	15	15	3	L11-NU200-1753	1470	F1
	400	~	~	125	250	350	20	50	3	L11-NU400-1753	2780	F2
	600	~	~	200	400	350	20	50	3	L11-NU600-1753	3900	F3
	800	~	~	200	500	500	~	~	3	L11-NU800-1753	5460	F4
	1200	~	~	200	500	500	~	~	3	L11-NU1200-1753	11900	F4

⑤ For Fuse Status Option
Add the following to List Price

L11-C30/J30	14
L11-J60/H30/H60	18

Ordering Instructions

- Specify Disconnect Switch catalog number (this page)
- Specify desired switch handle catalog number (page L30)
- Specify desired operating shaft catalog number (page L31)
- Specify desired accessories (starting on page L32)

- ① Time delay fuses may be required to utilize the disconnect switch at its maximum horsepower rating.
- ② Only UL listed Class CC, J and CSA Certified HRCI-J fuses are suitable for use with these disconnect switches.
- ③ Non-fused disconnect switches must use separately installed fuses for upstream short circuit protection.
- ④ 30A UL-rated device has I_{nsc} of 40 A per IEC. 60A UL-rated device has I_{nsc} of 80A per IEC.
- ⑤ To order a fusible switch with fuse status indicator on 30A and 60A switches, add an "S" to the end of the catalog number. For example, L11-J30-1753 changes to L11-J30-1753S. Not available on J100...J600, or L800 devices. Add \$18.00.

4th-Pole Modules (for 30A & 60A only) ④

Switch (typical)	Amp Rating (A)	Maximum Horsepower ❶							Fuses	Catalog Number	Price	Dimension Code
		1 Ø (60Hz)		Three Phase (60Hz)			DC					
		120V	240V	240V	480V	600V	125V	250V				
 L11-30-NJ  L11-30-NN	UL Class CC and CSA HRCI-MISC Fuses											
	30	2	3	7.5	15	20	3	5	30A CC, HRCI-Misc	L11-30-NC	76.90	A1
	UL Class J and CSA HRCI-J Fuses											
	30	2	3	7.5	15	20	3	5	30A J, HRCI-J	L11-30-NJ	76.90	A1
	60	3	10	15	30	50	5	10	60A J, HRCI-J	L11-60-NJ	96.30	B1
	CSA HRCII-C Fuses											
	30	2	3	7.5	15	20	~	~	30A HRCII-C	L11-30-NH	76.90	B1
	60	3	10	15	30	50	~	~	60A HRCII-C	L11-60-NH	90.80	B1
	Non-Fused											
	30 ❷	2	3	7.5	15	20	3	5	~	L11-30-NN	61.70	A2
60 ❸	3	10	15	30	40	5	10	~	L11-60-NN	80.30	B2	

Items in Gray available by Special Order only.


**④ For Fuse Status Option
Add the following to List Price**

L11-C30/J30	14
L11-J60/H30/H60	18

4th-Pole Modules
must be ordered
separately and field
installed to existing
L11 Disconnect
Switch.



L11-30-NN



L11-N30-1753

Replacement Mounting Hardware

Accessory	Description	Switch Dimension Code	Pkg Qty	Catalog Number	Price
	(1) set screw, (1) shaft clip, and (2) #8 M4 screws	A1, A2	2	L11-30-HDWR	3.22
	(1) set screw, (1) shaft clip, and (4) #8 M4 screws	B1, B2	4	L11-60-HDWR	4.70
	(8) HM10 25mm bolts, (8) HM10 nuts, (16) M10 washers	F1	1	L11-HF-200-4U	233.00
	(8) HM12 30mm bolts, (8) HM12 nuts, (16) M12 washers	F2	1	L11-HF-400-4U	369.00
	(8) HM10 16mm bolts, (8) HM10 washers	F6	1	L11-HF-250-3BDU	90.10
	(8) HM8 16mm bolts, (8) HM8 washers, (6) HM10 35mm bolts, (6) M10 nuts, (12) M10 washers	F7	1	L11-HF-400-3BU	369.00
	(8) HM12 30mm bolts, (8) HM12 washers	F8, F9	1	L11-HF-800-3U	249.00

① Time delay fuses may be required to utilize the disconnect switch at its maximum horsepower rating.

② 30A UL-rated device has I_{line} of 40 A per IEC.

③ 60A UL-rated device has I_{line} of 80A per IEC.

④ To order a 4th pole module for 30A or 60A switches with fuse status indicator, add an "S" to the end of the catalog number. For example, L11-30-NC changes to L11-30-NC_S. Not available on J100...J600, or L800 devices. Add \$18.00.

Switch Handle Assemblies (accepts 3 Padlocks)

Switch Handle Assembly ①②	Description	For use with	Color	Degree of Protection	Catalog Number	Price
 L11-PY	Padlockable Handle - Standard 80 x 114 mm - Configurable for defeatable or non-defeatable ③	L11-30...60A	Black	Type 3R, 3, 12, 4, 4X, IP66	L11-PB	48.10
			Red/Yellow	Type 3R, 3, 12, 4, 4X, IP66	L11-PY	48.10
 L11-PBT	Padlockable Handle - Test Mode 80 x 114 mm - Configurable for defeatable or non-defeatable ③	L11-30...60A	Black	Type 3R, 3, 12, 4, 4X, IP66	L11-PBT	50.90
			Red/Yellow	Type 3R, 3, 12, 4, 4X, IP66	L11-PYT	50.90
 L10-HM4	Padlockable Operating Handle Standard orientation with defeater	L11-100...400A	Black	Type 1, 3R, 12, 4, 4X – IP66	L10-HM4	96.20
			Red/Yellow	Type 1, 3R, 12, 4, 4X, IP66	L10-HM4E	96.20
 L10-HM4E-N2	Padlockable Operating handle Standard orientation without defeater	L11-100...400A	Black with light grey	Type 1, 3R, 12, 4, 4X – IP66	L10-HM4-N2	96.20
			Red/Yellow	Type 1, 3R, 12, 4, 4X – IP66	L10-HM4E-N2	96.20
 L11-HM4-L	Padlockable Operating Handle Standard orientation with defeater	L11-600...1200A	Black with light grey	Type 1, 3R, 12, 4, 4X, IP65	L11-HM4-L	129.00
			Red/Yellow	Type 1, 3R, 12, 4, 4X, IP65	L11-HM4E-L	129.00
 L11-HM4-N2-L	Padlockable Operating Handle Standard orientation without defeater	L11-600...1200A	Black with light grey	Type 1, 3R, 12, 4, 4X, IP65	L11-HM4-N2-L	129.00
			Red/Yellow	Type 1, 3R, 12, 4, 4X, IP65	L11-HM4E-N2-L	129.00




OSHA Lock Out/Tag Out Compliance (LOTO)


OSHA CFR36 Section 1910 mandates that disconnects be able to be locked out while in the OFF position during servicing. All L11 handles comply with this important safety requirement. *Please see NFPA Article 430 for disconnect requirements of motor applications.*

- ① Mounting screws included with Switch Handle Assembly.
- ② Lockable in OFF position (and ON position with special modification).
- ③ Switch handle can be field modified to be defeatable or non-defeatable.

Metal Operating Shafts ①

Shaft (typical)	For use with handle type...	Operating Shaft Length mm (in)	Catalog Number	Price
	L11-P/L11-P_T for L11-30...60A	305 (12)	L11-S1	20.20
		533 (21)	L11-S2	26.70
	L10-HM for L11 100...400A	320 (12.6)	L11-R7	45.90
		580 (22.8)	L11-R8	85.10
	L11-HM for fused L11 600...800A	320 (12.6)	L11-R11	49.40
		560 (22)	L11-R12	68.30
	L11-HM for Non-fused L11 600...1200A	320 (12.6)	L11-R9	58.90
		560 (22)	L11-R10	76.50
NFPA 79 Handle Kit - Internal handle that permits operation of the disconnect when the panel door is open, in compliance with NFPA79. • Includes NFPA 79 internal operating handle with shaft	L11-P/L11-P_T	305 (12)	L11-N1	84.20
		533 (21)	L11-N2	90.40
	L10-HM4 (L11 fused 100...400A)	320 (12.6)	L11-HM4-NFPA1	228.00
		560 (22)	L11-HM4-NFPA3	228.00
	L11-HM4_-L (L11 fused 600...800A)	320 (12.6)	L11-HM4-NFPA2	228.00
		560 (22)	L11-HM4-NFPA4	228.00

Operating Shaft Accessories

Accessory	Description	Switch Dimension Code	Pkg Qty	Catalog Number	Price
	Operating Shaft Coupler - Used with L11-S1 and L11-S2 shafts to extend shaft length an additional 120 mm (4.75 in).	A1, A2, B1, B2	1	L10-SC1	35.90


① See page L50 for Shaft dimensions.

② The L11-NU100...NU1200 Non-Fused switches do not have a means to be locked in the OFF position, therefore are not in compliance with NFPA79 and should not be used with L11-HM4-NFPA* handle kits.

Disconnect Switch Padlock Accessory (for 30A & 60A only) ①⑤




Accessory	Description	Switch Dimension Code	Pkg Qty	Catalog Number	Price
	Disconnect Switch Padlock Accessory	A1, A2, B1, B2	1	L11-PLA1	12.50

Replacement Fuse Carriers (for 30A & 60A only)

Accessory	Description	Pkg Qty	Without Fuse Status Indication		With Fuse Status Indication	
			Catalog Number	Price	Catalog Number	Price
 L11-J30-FC  Neon Fuse Status Indication L11-J30-FCS	30A CC Fuse Carrier	1	L11-C30-FC	24.30	L11-C30-FCS	32.10
	30A J Fuse Carrier	1	L11-J30-FC	24.30	L11-J30-FCS	32.10
	60A J Fuse Carrier	1	L11-J60-FC	32.10	L11-J60-FCS	42.90
	30A CSA HRCII-C Fuse Carrier	1	L11-H30-FC	23.30	L11-H30-FCS	31.20
	60A CSA HRCII-C Fuse Carrier	1	L11-H60-FC	31.20	L11-H60-FCS	41.60
	30A Non-Fuse Carrier	1	L11-N30-FC	21.50		
	60A Non-Fuse Carrier	1	L11-N60-FC	26.70		

Items in Gray are Special Order.

Auxiliary Contact Blocks

Accessory	Description	For use with ...	Contact Material	Pkg Qty	Catalog Number	Price
	Contact Block ②③ Note: Sold only in multiples of 10. Order (quantity of) 10 to receive one package of 10 pieces.	All L11-30...60A All Fusible switches L11-100...800A	N.O.	10	D7-X10	See Section H
			N.C.		D7-X01	
			N.O.E.M.		D7-X10E	
			N.C.L.B.		D7-X01L	
			N.O. w/ spring-clamp		D7-Q10	
			N.CO. w/ spring-clamp		D7-Q01	
	Auxiliary Contact Block ④ N.O.E.B./N.C.	All L11 Non-Fused 100...1200A		1	L11-1STNONC	14.10
				1	L11-2NDNONC	17.50

① For Padlock with ø3...6mm.

② Also used for test mode function on 30A...60A switches.

③ Maximum auxiliary contact blocks allowed to be mounted on switches:

- Max 6 for 30A...60A switches
- Max 4 for L11-J100...200A switches
- Max 8 for L11-J400...J600, & L800 switches

④ Only one auxiliary type can be mounted on switch. Auxiliaries cannot be combined.

⑤ Fusible L11-100...800A has built in lockable feature on switch.

Terminal Protective Covers ①②③

Accessory	Description	No. of poles Protected per pkg.	Mounting Position	Switch Dim. Code	Qty per Pkg	Pkg qty req. for Line & Load protection	Catalog Number	Price Each
 order 2 for 1 pkg of 2 shrouds	30A Terminal Shroud	6	line or load side	A1, A2	2	1	L11-30-C3	9.99
	60A Terminal Shroud	6	line or load side	B1, B2	2	1	L11-60-C3	13.80
 order 2 for 1 pkg of 2 shrouds	30A Terminal Shroud	2	line or load side	A1, A2	2	1	L11-30-C1	4.10
	60A Terminal Shroud	2	line or load side	B1, B2	2	1	L11-60-C1	5.51
								Pkg Price
 order 1 for 1 package of 3 shrouds	UL Terminal Shroud for L11-UL Fused 600A...800A	3	line or load side	F17	3	2 ③	L11-LNC29	102.00
	UL Terminal Shroud for L11-UL Fused 200A	3	line or load side	F6	3	2	L11-LNC31	158.00
	UL Terminal Shroud for L11 - UL Fused 400A	3	line or load side	F7	3	2	L11-LNC32	105.00
 1 shield covers all 3 poles	UL Terminal Shield for L11-UL Non-fused 100A...200A	3	line side	F1	1	1	L11-LNC17	30.70
		3	load side	F1	1	1	L11-LNC18	30.70
	UL Non-fused 400A	3	line side	F2	1	1	L11-LNC20	75.20
		3	load side	F2	1	1	L11-LNC21	75.20
	UL Non-fused 600A	3	line or load	F3	1	1 ③	L11-LNC23	109.00
	UL Non-fused 800A...1200A	3	line or load	F4	1	1 ③	L11-LNC25	146.00

Multi-Tap Terminal Lugs ①

Accessory	Description	Switch Dimension Code	Pkg Qty	Catalog Number	Pkg Price
	For 30A L11 Switches - Wire: (3) 8-14 AWG/1.5-10 mm² - Torque: 14 lb-in/1.6 Nm	A1, A2	1	L11-30-MTL3	26.00
	For 60A L11 Switches - Wire: (3) 4-14 AWG/2-25 mm² - Torque: 24 lb-in/2.8 Nm	B1, B2	1	L11-60-MTL3	31.20

③ L11 Switches include various protection covers as standard. See table to order optional shrouds/shields separately.

Switch Type	Terminal Shrouds	Terminal Shields	Terminal Lugs	Notes
L11-J30/60 A	N/A ②	N/A	Built-in	IP20 Touch-Safe by design
L11-J100 A	N/A	N/A	Built-in	IP20 Touch-Safe by design
L11-J200/400 A	Optional	N/A	Optional	Purchase optional items separately
L11-J600/L800 A	Includes 1 pkg L11-LNC29 for line side	N/A	Optional	Purchase optional items separately
L11-N30/60 A	N/A	N/A	Built-In	IP20 Touch-Safe by design
L11-NU100/400 A	N/A	Optional	Optional	Purchase optional items separately
L11-NU600 A	N/A	Includes 1 pkg L11-LNC23 for line side	Optional	Purchase optional items separately
L11-NU800/1200 A	N/A	Includes 1 pkg L11-LNC25 for line side	Optional	Purchase optional items separately

① Includes integral plastic cover (not shown), for IP10 ingress rating only.

② L11-XX-CX shrouds are typically used to re-label power terminals when rotating the switch 180°.

Terminal Lug Kits ❶

Accessory	For use with...	Wire Size	Pkg Qty	Catalog Number	Pkg Price
 order 1 for 1 package of 3 lugs	L11-J200 Fused L11-NU100, L11-NU200 Non-Fused	(1) #6 - 300 MCM	3	L11-TL1	42.80
 order 1 for 1 package of 3 lugs	L11-J400 Fused L11-NU400 Non-Fused	(1) #4 - 600 MCM	3	L11-TL3	146.00
 order 1 for 1 package of 3 lugs	L11-J400 Fused L11-NU400 Non-Fused	(2) #6 - 350 MCM	3	L11-TL5	198.00
	L11-J600...L800 Fused L11-NU600 Non-Fused	(2) #2 - 600 MCM	3	L11-TL7	248.00
 order 1 for 1 package of 6 lugs	L11-NU800...NU1200 Non-Fused	(2) #2 - 600 MCM	6	L11-TL9	682.00

❶ L11-30/60 Fused and Non-fused, and L11-J100 Fused disconnect switches are equipped with built-in terminal lugs.

L11 Enclosed Motor Disconnects (UL and CSA Approved Enclosures)

Amp/Horsepower Rating						Type 3/4/12 Watertight, Dusttight Sheetmetal Enclosure			Type 4/4X Watertight, Corrosion-Resistant Stainless Steel Enclosure			Type 4/4X Watertight, Corrosion-Resistant Non-metallic Enclosure		
														
UL/ CSA Amps	Horsepower					Catalog Number	Price	Dimension Code	Catalog Number	Price	Dimension Code	Catalog Number	Price	Dimension Code
	1Ø (60 Hz)		3Ø (60 Hz)											
	120V	240V	240V	480V	600V									
Class CC Fused														
30	2	3	7.5	15	20	L11-FC030P3	774	A1	L11-CC030P3	918	A1	L11-KC030P3	777	A1
Class J Fused														
30	2	3	7.5	15	20	L11-FJ030P3	718	A1	L11-CJ030P3	918	A1	L11-KJ030P3	796	A1
60	3	10	15	30	50	L11-FJ060P3	851	B1	L11-CJ060P3	1000	B1	L11-KJ060P3	986	B1
100	7.5	15	30	60	75	L11-FJ100P3	1342	C1	L11-CJ100P3	2525	C1	L11-KJ100P3	1342	C1
200	~	25	60	125	150	L11-FJ200P3	2238	D1	L11-CJ200P3	3460	D1	L11-KJ200P3	2237	D1
400	~	50	125	250	350	L11-FJ400P3	4123	F1	L11-CJ400P3	6615	F1	L11-KJ400P3	4122	F1
Non-Fused														
30	2	3	7.5	15	20	L11-FN030P3	525	A2	L11-CN030P3	989	A2	L11-KN030P3	525	A2
60	3	10	15	30	50	L11-FN060P3	930	B2	L11-CN060P3	1252	B2	L11-KN060P3	930	B2
100	7.5	15	30	75	100	L11-FN100P3	1342	C1	L11-CN100P3	2462	C1	L11-KN100P3	1342	C1
200	~	50	75	150	200	L11-FN200P3	2238	D1	L11-CN200P3	3460	D1	L11-KN200P3	2237	D1
400	~	~	125	250	350	L11-FN400P3	4123	F1	L11-CN400P3	6615	F1	L11-KN400P3	4122	F1

Larger sizes available. Contact your Sprecher + Schuh representative.

Enclosed Disconnect Assemblies Include:

- Disconnect Switch
- Black handle/shaft with ON/OFF marking. For a yellow and red handle, add suffix "E" to the end of the catalog number. Example: change L11-FN030P3 to L11-FN030P3E.
- Line & Load Terminal Lugs for Fused 200/400A & Non-Fused 100A...400A (Lugs are built-in on Fused 30/60/100A & Non-fused 30/60A switches).
- Two Ground Lugs mounted on back-panel

NOTE: Fusible accessory Shrouds, Non-Fusible accessory Shields must be purchased separately and installed by user. To add any accessory items into these standard assemblies, please contact your Sprecher+Schuh representative for a custom enclosed L11 request.



L11-KJ060P3

Applications Within the United States and Canada

General

The requirements for disconnect switches used in motor branch circuits rated 600V and less are defined in Article 430, Part J of the U.S. National Electrical Code (NEC), NFPA70. Canadian Electrical Code (CEC) requirements are very similar in the area of motor branch circuit disconnect requirements. For simplicity, we will treat the NEC and CEC requirements as being the same – and reference specific sections of the US National Electrical Code.

The requirements for properly sizing a disconnect switch are dependent on the type of application. The NEC refers to two types of applications: single motor and combination loads. A combination load consists of an application where two or more motors are used together or where one or more motors are used in combination with other loads, such as resistance heaters.

Single Motor Applications

Section 430-110 Paragraph (a) states that the disconnect switch must have an ampere rating of at least 115% of the full load current rating of the motor.

Example 1: for a motor with a full-load current of 22A, the disconnect switch must be rated at least 25.3A (22×1.15).

If the disconnecting means under evaluation is rated in horsepower, the selection of the disconnect switch is even more straightforward; a disconnect switch must have a horsepower rating equal to, or greater than the horsepower rating of the motor at the applicable voltage.

Example 2: For a motor with a 10HP rating at 460V AC, the disconnect switch must be rated at least 10HP at 460V AC.

If the disconnect switch is rated in horsepower, and UL Listed, UL Component Recognized, or CSA Certified, it will meet the requirements for the 115% full-load current rating stipulated by the NEC.

Combination Load Applications

Section 430-110 Paragraph (c) addresses the rating of the disconnecting means for combination loads. This paragraph essentially requires that the loads that “may be simultaneously on a single disconnecting means” be combined to provide equivalent full-load and locked-rotor currents for what is then to be considered as a single motor for the purpose of selecting the appropriate disconnecting means. This means that it is necessary to identify the particular combination of connected loads which can be operating simultaneously and will result in the maximum full-load and locked-rotor current sums.

The individual full-load current values are to be selected from Tables 430-148, 430-149, or 430-150 and the locked-rotor values are to be from Table 430-151.

The equivalent single motor full-load current is the sum of the simultaneously operating motor full-load currents and the rating in amperes of the other loads operating at the same time. The equivalent locked-rotor

current is the sum of the simultaneously started motors’ locked-rotor currents and the full-load currents of the remaining operating motor and non-motor loads.

The disconnecting means shall have a current rating equal to or greater than 115% of the equivalent single motor full-load current and have a horsepower rating equal to or greater than the horsepower rating determined from the equivalent locked-rotor summation.

Consider the following 460V application:

Load	HP	Full-Load Current A
Motor 1	5	7.6 (simultaneous)
Motor 2	10	14.0 (not included) ①
Motor 3	15	21.0 (simultaneous)
Motor 4	20	27.0 (simultaneous)
Other		7.0 (simultaneous)
Total Equivalent		62.6 (simultaneous)

① Motor 2 is not included in the total since it cannot operate simultaneously with the other motor, therefore, the disconnect switch must be rated at least 72A (1.15×62.6).

Consider now the locked-rotor current analysis for the same application:

Load	HP	Locked Rotor Current A
Motor 1	5	(7.6 FLA) 45.6 (simultaneous)
Motor 2	10	84.0 (not included) ①
Motor 3	15	126.0 (simultaneous) ②
Motor 4	20	162.0 (simultaneous) ②
Other		7.0 (simultaneous)
Total Equivalent		302.6 (simultaneous)

① Note again that Motor 2 cannot operate simultaneously with the other loads.

② The largest equivalent locked-rotor current occurs when motors 3 and 4 start together while the other loads marked “simultaneous” are already operating. Since Motor 1 is not starting with Motors 3 and 4, its full-load current will be added to the total instead of its locked-rotor current.

Table 430-151, which provides the correlation between locked-rotor currents and HP ratings, shows that a 40 HP rating is the equivalent for 302.6 locked-rotor amperes.

Therefore, the disconnect selected for this application must have a current rating of at least 72A and a HP rating of at least 40 HP. In this case, an L10 disconnect switch rated for 100A and 60 HP at 460V would be an appropriate choice. What can be seen from this analysis is that, depending upon the number of motors that can start simultaneously, the actual size of the required disconnect is sometimes determined by the equivalent full load current (72A) and other times by the equivalent horsepower determined from the locked-rotor analysis (40 HP).

Fused Disconnect Switches for UL Class Fuses and CSA HRCI-J

Electrical Ratings				L11-C30-1753		L11-J30-1753		L11-J60-1753	
UL Fuse Type / CSA Fuse Type				Class CC/HRCI-MISC ❶		Class J/HRCI-J		Class J/HRCI-J	
Maximum Fuse Cartridge Size (A)				30		30		60	
Maximum Voltage		AC	(V)	600		600		600	
		DC	(V)	250		250		250	
Ampere Rating (A)				30		30		60	
Maximum Short Circuit Prospective Fault Current (kA)				200		200		200	
Fuse Operating Characteristics				Time Delay	Non-Time Delay	Time Delay	Non-Time Delay	Time Delay	Non-Time Delay
Maximum Hp, 3Ø AC	200V 60 Hz	(Hp)	5	3	7.5	3	15	7.5	
	240V 60 Hz	(Hp)	5	3	7.5	3	15	7.5	
	480V 60 Hz	(Hp)	10	5	15	5	30	15	
	600V 60 Hz	(Hp)	10	7.5	20	7.5	50	15	
Maximum Hp, 1Ø AC	120V, 60 Hz	(Hp)	0.75	0.5	2	0.5	3	1.5	
	240V, 60 Hz	(Hp)	2	1.5	3	1.5	10	3	
Maximum Hp, DC	125V, DC	(Hp)	2	3	3	2	5	5	
	250V, DC	(Hp)	3	5	5	5	10	10	

Mechanical Data			L11-C30-1753		L11-J30-1753		L11-J60-1753	
Degree of Protection (per IEC 60947-3)								
Switch Only			IP20		IP20		IP20	
Switch with Terminal Shield & Fuse Carriers			IP20		IP20		IP20	
Mechanical Endurance ❷		Operations	10,000		10,000		10,000	
Handle Mechanism Operating Torque	N•m		3.5		3.5		3.5	
	lb•in		35		35		35	
Terminal Capacity								
Power Terminals	mm²		2.5...10		2.5...10		2.5...25	
	AWG		#14...#8		#14...#8		#14...#4	
Auxiliary Contact Terminals	mm²		2.5...4		2.5...4		2.5...4	
	AWG		#14...#12		#14...#12		#14...#12	
Maximum Number of Auxiliary Contacts			6		6		6	
Approximate Weight	kg		0.92		0.92		1.32	
	lbs		2.03		2.03		2.9	
Minimum Enclosure Size		Height	248 (9-3/4)		248 (9-3/4)		248 (9-3/4)	
Approximate dimensions in millimeters (inches)		Width	171 (6-3/4)		171 (6-3/4)		197 (7-3/4)	
		Depth	148 (5-13/16)		148 (5-13/16)		148 (5-13/16)	
Switch Dimensions Reference (See dimension drawings)			A1		A1		B1	

❶ CSA HRCI-MISC fuses must also be UL Listed as Class CC fuses.

❷ Based on Sprecher + Schuh tests in accordance with the requirements as defined in CSA C22.2 No. 4, IEC 60947-3, and UL 98.

Fused Disconnect Switches for UL Class Fuses and CSA HRCI-J

Electrical Ratings			L11-J100-1753	L11-J200-1753	L11-J400-1753	L11-J600-1753	L11-L800-1753
UL Fuse Type / CSA Fuse Type			Class J/HRCI-J				Class L
Maximum Fuse Cartridge Size	(A)		100	200	400	600	800
Maximum Voltage	AC (V)		600	600	600	600	600
	DC (V)		250 ②	250 ②	250 ②	250 ②	250 ②
Ampere Rating	(A)		100	200	400	600	800
Maximum Short Circuit Prospective Fault Current	(kA)		200	200	200	200	200
Fuse Operating Characteristics							
Maximum Hp, 3Ø AC	200V 60 Hz (Hp)		~	~	~	~	~
	240V 60 Hz (Hp)		30	60	125	200	200
	480V 60 Hz (Hp)		60	125	250	400	500
	600V 60 Hz (Hp)		75	150	350	500	500
Maximum Hp, 1Ø AC	120V, 60 Hz (Hp)		7.5	~	~	~	~
	240V, 60 Hz (Hp)		15	25	50	~	~
Maximum Hp, DC	125V, DC (Hp)		7.5	15	20	~	~
	250V, DC (Hp)		20	40	50	~	~

Mechanical Data			L11-J100-1753	L11-J200-1753	L11-J400-1753	L11-J600-1753	L11-L800-1753
Degree of Protection (per IEC 60947-3)							
Switch Only			IP20	IP20	IP20	IP20	IP20
Switch with Terminal Shield & Fuse Carriers			IP20	IP20	IP20	IP20	IP20
Mechanical Endurance ①	Operations		10,000	8,000	6,000	5,000	5,000
Handle Mechanism Operating Torque	N•m		10	15	20	70	70
	lb•in		88.5	132.8	177	620	620
Terminal Capacity							
Power Terminals	mm²			300 MCM	600 MCM; 2 x 300 MCM	2 x 600 MCM	2 x 600 MCM
	AWG		#1	#6	#2 or 2 x #6	2 x #2	2 x #2
Auxiliary Contact Terminals	mm²		2.5...4	2.5...4	2.5...4	2.5...4	2.5...4
	AWG		#14...#12	#14...#12	#14...#12	#14...#12	#14...#12
Maximum Number of Auxiliary Contacts			4	8	8	8	8
Approximate Weight	kg		2.4	3.6	4.85	20	20
	lbs		5.3	7.9	10.7	44	44
Minimum Enclosure Size	Height						
	Width		~	~	~	~	~
	Depth						
Switch Dimensions Reference (See dimension drawings)			F5	F6	F7	F8	F9

① Based on Sprecher + Schuh tests in accordance with the requirements as defined in CSA C22.2 No. 4, IEC 60947-3.

② 3-Poles in series.

Non-Fused Disconnect Switches for CSA and UL Class Applications ❶

Electrical Ratings			L11-N30-1753		L11-N60-1753		L11-NU100-1753	L11-NU200-1753
Maximum Voltage	AC (V)		600		600		600	600
	DC (V)		250		250		250	250
Fuse Type			~		~		J	J
Ampere Rating		(A)	30 ❷		60 ❷		100	200
Maximum Short Circuit Prospective Fault Current		(kA)	200		200		200	200
Fuse Operating Characteristics ❸			Time Delay	Non-Time Delay	Time Delay	Non-Time Delay	~	~
Maximum Hp, 3Ø AC	200V 60 Hz	(Hp)	7.5	3	15	7.5	~	~
	240V 60 Hz	(Hp)	7.5	3	15	7.5	30	75
	480V 60 Hz	(Hp)	15	5	30	15	75	150
	600V 60 Hz	(Hp)	20	7.5	50	15	100	200
Maximum Hp, 1Ø AC	120V, 60 Hz	(Hp)	2	0.5	3	1.5	7.5	~
	240V, 60 Hz	(Hp)	3	1.5	10	3	15	50
Maximum Hp, DC	125V, DC	(Hp)	3	2	5	5	10	15
	250V, DC	(Hp)	5	5	10	10	15	15
Power Lost		(W)	2		6		~	~

Mechanical Data		L11-N30-1753	L11-N60-1753	L11-NU100-1753	L11-NU200-1753
Degree of Protection (per IEC 60947-3)					
Switch Only		IP20	IP20	IP20	IP20
Switch with Terminal Shield & Fuse Carriers		IP20	IP20	IP20	IP20
Mechanical Endurance ⓘ	Operations	10,000	10,000	10,000	10,000
Handle Mechanism Operating Torque	N•m	3.5	3.5	10	10
	lb•in	35	35	88.5	88.5
Terminal Capacity					
Power Terminals	mm²	2.5...10	2.5...25	300 MCM	300 MCM
	AWG	#14...#8	#14...#4	#6	#6
Auxiliary Contact Terminals	mm²	2.5...10	2.5...25	~	~
	AWG	#14...#8	#14...#4		
Maximum Number of Auxiliary Contacts		6	6	2	2
Approximate Weight	kg	0.81	1.14	1.67/2.1	1.67/2.1
	lbs	1.78	2.52	3.7/4.3	3.7/4.3
Minimum Enclosure Size	Height	248 (9-3/4)	248 (9-3/4)		
Approximate dimensions in millimeters (inches)	Width	171 (6-3/4)	197 (7-3/4)	~	~
	Depth	111 (4-3/8)	111 (4-3/8)		
Switch Dimensions Reference (See dimension drawings)		A2	B2	F1	F1

❶ Non-fused disconnect switches must be used with separately installed fuses.

❷ When using CSA HRCI-J, HRCI-MISC (also UL Listed as Class CC) or HRCI-T fuses, and UL Class J, CC or T fuses.

❸ Based on Sprecher + Schuh tests in accordance with the requirements as defined in CSA C22.2 No. 4, IEC 60947-3, UL 1087 and UL 98.

Non-Fused Disconnect Switches for CSA and UL Class Applications ❶

Electrical Ratings			L11-NU400-1753	L11-NU600-1753	L11-NU800-1753	L11-NU1200-1753
Maximum Voltage	AC	(V)	600	600	600	600
	DC	(V)	250	250	250	250
Fuse Type			J	J	L	L
Ampere Rating		(A)	400	600	800	1200
Maximum Short Circuit Prospective Fault Current		(kA)	200	200	100	100
Fuse Operating Characteristics ❸			~	~	~	~
Maximum Hp, 3Ø AC	200V 60 Hz	(Hp)	~	~	~	~
	240V 60 Hz	(Hp)	125	200	200	200
	480V 60 Hz	(Hp)	250	400	500	500
	600V 60 Hz	(Hp)	350	350	500	500
Maximum Hp, 1Ø AC	120V, 60 Hz	(Hp)	~	~	~	~
	240V, 60 Hz	(Hp)	~	~	~	~
Maximum Hp, DC	125V, DC	(Hp)	20	20	~	~
	250V, DC	(Hp)	50	50	~	~
Power Lost		(W)	~	~	~	~

Mechanical Data			L11-NU400-1753	L11-NU600-1753	L11-NU800-1753	L11-NU1200-1753
Degree of Protection (per IEC 60947-3)						
Switch Only			IP20	IP20	IP20	IP20
Switch with Terminal Shield & Fuse Carriers			IP20	IP20	IP20	IP20
Mechanical Endurance ❸ Operations			6,000	6,000	3,500	3,500
Handle Mechanism Operating Torque	N•m		14.5	37	50	50
	lb•in		128.3	327.5	442	442
Terminal Capacity						
Power Terminals	mm²		600 MCM	2 x 600 MCM	4 x 600 MCM	4 x 600 MCM
	AWG		#2	2 x #2	4 x #2	4 x #2
Auxiliary Contact Terminals			mm²	~	~	~
			AWG	~	~	~
Maximum Number of Auxiliary Contacts			2	2	2	2
Approximate Weight	kg		3/3.8	8.2/10.3	11.6/14.5	11.6/14.5
	lbs		6.6/8.4	18.1/22.7	25.6/32	25.6/32
Minimum Enclosure Size	Height					
	Width		~	~	~	~
	Depth					
Switch Dimensions Reference (See dimension drawings)			F2	F3	F4	F4

❶ Non-fused disconnect switches must be used with separately installed fuses.

❷ When using CSA HRCI-J, HRCI-MISC (also UL Listed as Class CC) or HRCI-T fuses, and UL Class J, CC or T fuses.

❸ Based on Sprecher + Schuh tests in accordance with the requirements as defined in CSA C22.2 No. 4, IEC 60947-3, UL 1087 and UL 98.

Fused Disconnect Switches for CSA HRCII-C Fuses

Electrical Ratings			L11-H30-1753	L11-H60-1753
CSA Fuse Type/UL Fuse Type			HRCII-C	HRCII-C
Maximum Fuse Cartridge Size	(A)		30	60
Maximum Voltage	AC (V)		600	600
Ampere Rating	(A)		30	60
Maximum Short Circuit Prospective Fault Current	(kA)		200	200
Fuse Operating Characteristics				
Maximum Hp, 3Ø AC	200V 60 Hz	(Hp)	7.5	15
	240V 60 Hz	(Hp)	7.5	15
	480V 60 Hz	(Hp)	15	30
	600V 60 Hz	(Hp)	20	50
Maximum Hp, 1Ø AC	120V, 60 Hz	(Hp)	2	3
	240V, 60 Hz	(Hp)	3	10

Mechanical Data			L11-H30-1753	L11-H60-1753
Degree of Protection (per IEC 60947-3)				
Switch Only			IP20	IP20
Switch with Terminal Shield & Fuse Carriers			IP20	IP20
Mechanical Endurance ❶	Operations		10,000	10,000
Handle Mechanism Operating Torque	N•m		3.5	3.5
	lb•in		35	35
Terminal Capacity				
Power Terminals	mm²		2.5...10	2.5...25
	AWG		#14...#8	#14...#4
Auxiliary Contact Terminals	mm²		2.5...4	2.5...4
	AWG		#14...#12	#14...#12
Maximum Number of Auxiliary Contacts			6	6
Approximate Weight	kg		1.18	1.18
	lbs		2.60	2.60
Minimum Enclosure Size	Height		248 (9-3/4)	248 (9-3/4)
	Width		171 (6-3/4)	197 (7-3/4)
	Depth		148 (5-13/16)	148 (5-13/16)
Switch Dimensions Reference (See dimension drawings)			B1	B1

❶ Based on Sprecher + Schuh tests in accordance with the requirements as defined in CSA C22.2 No. 4, IEC 60947-3, UL 1087 and UL 98.

Environmental Data For All L11 Fused and Non-Fused Disconnect Switches

Environmental Ratings		L11- _30A...60A	L11- _100A...1200A ①
Ambient Temperature			
Open	[°C (F)]	-20...+55 (-4...+131)	-20...+70 (-4...+158)
Enclosed	[°C (F)]	-20...+40 (-4...+104)	-20...+70 (-4...+158)
Storage	[°C (F)]	-40...+65 (-40...+149)	-25...+70 (-13...+158)
Altitude (per IEC 60947-1)	[m]	2,000	2,000
Relative Humidity (per IEC 60947-1)		90% at +20°C (+68°F)	90% at +20°C (+68°F)
		50% at +40°C (+104°F)	50% at +40°C (+104°F)
Auxiliary Contact Ratings:			
D7 Contact Ratings		See Section H	
L11-1STNONC and L11-2NDNONC			
AC Rating (100mA min. load)		10.1A at 250V AC 1/2 HP at 250V AC 1/4 HP at 125V AC	
DC Rating (100mA min. load)		0.5A at 125V DC	
DC-13 General use (no HP ratings)		0.25A at 250V DC	

Standards Compliance

IEC 60947-4-1/EN60947-3
BS EN60947-3
VDE 0660
CSA 22.2 No. 4
NEMA KS-1
UL 98

with L11-SDK2 Handle Kit

UL 98
CSA 22.2 No. 4

Certifications

UL Listed (File No. E 47426, Guide WHTY)
CSA Certified (File No. LR1234)
CE
ASTA Certified
LOVAG Certified


with L11-SDK2 Handle Kit

UL Listed (File No. E47426, Guide WHTY)
CSA Certified (File No. LR1234)

CSA HRCII Fuses (sold by others)

Dimensions in millimeters (inches). Dimensions are not intended to be used for manufacturing purposes.

- CSA fuse type: HRCII-C
- Voltage rating: 600V AC
- Interrupting rating: 200 000 A
- Standard cartridge sizes: 30, & 60 A
- Typical ampere ratings: 1...60 A
- Construction: Blade type for bolted connection
- Can be installed on Bulletin 194R disconnect switch
- Cat. Nos: L11-H30-1753, L11-H60-1753
- Where used: Canada




Current Range [A]	A	B	C	D	E	F	G	H	J
0...30	84.14 (3-5/16)	71.04 (2-51/64)	50.8 (2)	20.64 (13/16)	8.73 (11/32)	7.54 (19/64)	5.56 (7/32)	23.81 (15/16)	1.59 (1/16)
31...60	88.9 (3-1/2)	71.04 (2-51/64)	50.8 (2)	20.64 (13/16)	12.7 (1/2)	7.54 (19/64)	5.56 (7/32)	26.99 (1-1/16)	1.59 (1/16)

① Derate switch 1% for every 1°C over 40°C

CSA HRCI Class CC Fuses (sold by others)





Dimensions in millimeters (inches). Dimensions are not intended to be used for manufacturing purposes.

- UL fuse type: Class CC
- CSA fuse type: HRCI-MISC
- Voltage rating: 600V AC
- Interrupting rating: 200 000 A
- Standard cartridge sizes: 30 A
- Typical ampere ratings: 1...30 A
- Construction: Ferrule type
- Can be installed on L11-C30-1753 disconnect switch
- Where used: North America


CSA HRCI Class J Fuses (sold by others)

Dimensions in millimeters (inches). Dimensions are not intended to be used for manufacturing purposes.

- CSA fuse type: HRCI-J
- UL fuse type: Class J
- Voltage rating: 600V AC
- Interrupting rating: 200 000 A
- Standard cartridge sizes: 30, 60, 100, 200, and 400 A
- Typical ampere ratings: 1...600 A; Blade type for bolted connection
- Can be installed on L11 disconnect switch
- Cat. Nos: L11-J30...J400-1753
- Where used: North America




Wiring Diagrams

UL Listed, CSA Certified	Dimension Reference	Circuit
L11-C30-1753 L11-J30-1753 L11-J60-1753 L11-H30-1753 L11-H60-1753	A1 A1 B1 B1 B1	
L11-N30-1753 L11-N60-1753	A2 B2	
L11-*1753 + L11-*NC/NJ/NH	3-Pole Switch + 4-Pole Module	

L11 Fused and Non-Fused Disconnect Switches (30 & 60A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.




Dimension Reference	Approximate Dimensions in mm (in)							
	H	W	D	A	B	C ❶	E ❶	FD
A1	108 (4-1/4)	120 (4-3/4)	101 (4)	90 (3-9/16)	105 (4-1/8)	85 (3-11/32)	82 (3-15/64)	2-M4, 2-#8
A2	108 (4-1/4)	120 (4-3/4)	80 (3-1/8)	90 (3-9/16)	105 (4-1/8)	85 (3-11/32)	82 (3-15/64)	2-M4, 2-#8
B1	113 (4-29/64)	142 (5-19/32)	114 (4-31/64)	100 (3-15/16)	120 (4-23/32)	N/A	N/A	4-M4, 4-#8
B2	113 (4-29/64)	142 (5-19/32)	93 (3-43/64)	100 (3-15/16)	120 (4-23/32)	N/A	N/A	4-M4, 4-#8


❶ Mounting holes are backward compatible with L10 Disconnect Switches

L11 Fused Disconnect Switches (100A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.




L11 Fused Disconnect Switches (200A)




L11 Fused Disconnect Switches (400A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.




L11 Fused Disconnect Switches (600...800A)



L11 Non-Fused Disconnect Switches (100...400A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.




L11-N...	Dim. Ref.	Approximate Dimensions in mm (in)													
		Overall		Terminal Shrouds		Switch Body					Switch Mounting				
		C	AC	AD	F (3-pole)	F (4-pole)	H	J1 (3-pole)	J1 (4-pole)	K	M (3-pole)	M (4-pole)	N	R1	R2
100	F1	94.6 (3.72)	256 (10.1)	77.5 (3.05)	180 (7.09)	230 (9.06)	107 (4.22)	55 (2.17)	105 (4.13)	45.6 (1.8)	160 (6.3)	210 (8.7)	135 (5.31)	9 (0.35)	7 (0.27)
200		94.6 (3.72)	256 (10.1)	77.5 (3.05)	180 (7.09)	230 (9.06)	107 (4.22)	55 (2.17)	105 (4.13)	45.6 (1.8)	160 (6.3)	210 (8.7)	135 (5.31)	9 (0.35)	7 (0.27)
400	F2	128 (4.92)	406 (16)	115 (4.15)	230 (9.05)	290 (11.4)	166 (6.53)	75 (2.95)	135 (5.31)	67.5 (2.65)	210 (8.26)	270 (10.6)	195 (7.67)	9 (0.35)	7 (0.27)

L11-N...	Dim. Ref.	Approximate Dimensions in mm (in)							
		Connection							
		T	U	V	W	Y	Z	AA	AB
100	F1	50 (1.97)	25 (0.98)	30 (1.18)	11 (0.43)	3.5 (0.14)	34.4 (0.14)	160 (6.3)	15 (0.6)
200		50 (1.97)	25 (0.98)	30 (1.18)	11 (0.43)	3.5 (0.14)	34.4 (0.14)	160 (6.3)	15 (0.6)
400	F2	65 (2.56)	45 (1.77)	50 (1.97)	13 (0.51)	5 (0.2)	53 (2.08)	260 (10.2)	20 (0.8)

L11 Non-Fused Disconnect Switches (600A)


Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Approximate Dimensions in mm (in)													
L11-N...	Dim. Ref.	Terminal Shrouds	Switch Body					Switch Mounting				Connection	
		AC	F (3-pole)	F (4-pole)	H	J (3-pole)	J (4-pole)	M (3-pole)	M (4-pole)	N	N1	AA	Z
600	F3	460 (18.12)	280 (11)	360 (14.17)	140 (5.5)	127.5 (5)	167.5 (6.59)	255 (10.03)	335 (13.19)	175 (6.88)	59.5 (2.34)	320 (12.6)	47 (1.85)

L11 Non-Fused Disconnect Switches (800...1200A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Approximate Dimensions in mm (in)													
L11-N...	Dim. Ref.	Terminal Shrouds	Switch Body					Switch Mounting				Connection	
		AC	F (3-pole)	F (4-pole)	H	J (3-pole)	J (4-pole)	M (3-pole)	M (4-pole)	N	N1	AA	Z
800	F4	460 (18.12)	372 (14.64)	492 (19.37)	140 (5.5)	173.5 (6.83)	233.5 (9.19)	347 (13.66)	467 (18.38)	175 (6.88)	59.5 (2.34)	330 (13)	47 (1.85)
1200		460 (18.12)	372 (14.64)	492 (19.37)	140 (5.5)	173.5 (6.83)	233.5 (9.19)	347 (13.66)	467 (18.38)	175 (6.88)	59.5 (2.34)	330 (13)	47 (1.85)

L11 Metal Operating Shaft Dimensions




L11-S1..S2



L11-R7..R8



L11-R9..R12





Typical View


Catalog Number	A ² mm (in)	B mm (in)	C mm (in)
L11-S1	6.35 (0.238)	305 (12)	
L11-S2	6.35 (0.238)	533 (21)	
L11-R7	10 (0.39)	320 (12.6)	~
L11-R8	10 (0.39)	580 (22.8)	~
L11-R9	12 (0.47)	320 (12.6)	22 (0.87)
L11-R10	12 (0.47)	560 (22)	22 (0.87)
L11-R11	12 (0.47)	320 (12.6)	22 (0.87)
L11-R12	12 (0.47)	560 (22)	22 (0.87)

L11-P*/L11-P*T Operating Handles


Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



OR




L10-HM4/HM4E Operating Handles




Operating Handles — Cat. No. L10-HM4, -HM4E

L11-HM4*-L/-N2-L Operating Handles



L11-N1 & L11-N2 Operating Handle (30 & 60A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.




Next Generation L11			
Disconnect	C	D	
L11-N30-__	≥ 165 mm 6.5 in	155 mm 6.0 in	
L11-B20-__ L11-B32-__ L11-C30-__ L11-F25-__ L11-F32-__ L11-J30-__	≥ 190 mm 7.5 in		
L11-N60-__	≥ 180 mm 7.0 in		170 mm 6.75 in
L11-B63-__ L11-D32-__ L11-D63-__ L11-F63-__ L11-H30-__ L11-H60-__ L11-J60-__	≥ 205 mm 8.0 in		

Legacy L10			
Disconnect	C	D	
L10-NN030__	≥ 170 mm 6.75 in	140 mm 5.5 in	
L10-NC030__ L10-NJ030__ L10-NA100__ L10-NA200__	≥ 210 mm 8.25 in		
L10-NN060__	≥ 170 mm 6.75 in		115 mm 4.5 in
L10-NJ060__ L10-NA300__	≥ 210 mm 8.25 in		

L11 Enclosure and Operating Handle Dimensions


Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Catalog Number	Dimension Reference	A	B	C		D	E	F	
		Maximum	Minimum	Minimum	Maximum	Minimum	Minimum	Minimum	Maximum
L11-C30-1753	A1	171 (6-3/4)	45 (1-49/64)	147.6 (5-13/16)	454 (17-7/8)	248 (9-3/4)	89 (3-1/2)	1.4 (1/16)	4/78 (3/16)
L11-J30-1753		171 (6-3/4)	45 (1-49/64)	111 (4-3/8)	454 (17-7/8)	248 (9-3/4)	89 (3-1/2)	1.4 (1/16)	4/78 (3/16)
L11-N30-1753	A2	171 (6-3/4)	45 (1-49/64)	111 (4-3/8)	454 (17-7/8)	248 (9-3/4)	89 (3-1/2)	1.4 (1/16)	4/78 (3/16)
L11-J60-1753	B1	197 (7-3/4)	45 (1-49/64)	147.6 (5-13/16)	454 (17-7/8)	248 (9-3/4)	105 (4-9/64)	1.4 (1/16)	4/78 (3/16)
L11-H30-1753		197 (7-3/4)	45 (1-49/64)	147.6 (5-13/16)	454 (17-7/8)	248 (9-3/4)	105 (4-9/64)	1.4 (1/16)	4/78 (3/16)
L11-H60-1753		197 (7-3/4)	45 (1-49/64)	111 (4-3/8)	454 (17-7/8)	248 (9-3/4)	105 (4-9/64)	1.4 (1/16)	4/78 (3/16)
L11-N60-1753	B2	197 (7-3/4)	45 (1-49/64)	111 (4-3/8)	454 (17-7/8)	248 (9-3/4)	105 (4-9/64)	1.4 (1/16)	4/78 (3/16)

L11 Enclosure Installation Dimensions


Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Catalog Number	Dimension Reference	A1 Min.	A2 Min.	B Min.	B Min.	C Min.	C Max.	D Min.	E Min.	F Min.	F Max.
L11-C30-1753 L11-J30-1753	A1	171 (6-3/4)	203 (7-63/64)	45 (1-49/64)	76 (3)	178 (7)	454 (17-7/8)	248 (9-3/4)	89 (3-1/2)	1.4 (1/16)	4.78 (3/16)
L11-N30-1753	A2	171 (6-3/4)	203 (7-63/64)	45 (1-49/64)	76 (3)	178 (7)	454 (17-7/8)	248 (9-3/4)	89 (3-1/2)	1.4 (1/16)	4.78 (3/16)
L11-J60-1753 L11-H30-1753 L11-H60-1753	B1	197 (7-3/4)	228 (8-63/64)	45 (1-49/64)	76 (3)	178 (7)	454 (17-7/8)	248 (9-3/4)	105 (4-9/64)	1.4 (1/16)	4.78 (3/16)
L11-N60-1753	B2	197 (7-3/4)	228 (8-63/64)	45 (1-49/64)	76 (3)	178 (7)	454 (17-7/8)	248 (9-3/4)	105 (4-9/64)	1.4 (1/16)	4.78 (3/16)


Type 3/4/12 - Watertight, Dusttight Sheet Metal Enclosure (30 & 60A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Amps	Type	Dim. Ref.	A	B	C	D	E	F
30	Fused & Non-fused	A1, A2	305 (12.00)	305 (12.00)	173 (6.80)	224 (8.81)	267 (10.5)	267 (10.5)
60	Fused & Non-fused	B1, B2	305 (12.00)	305 (12.00)	173 (6.80)	224 (8.81)	267 (10.5)	267 (10.5)


Type 4/4X Watertight, Corrosion-Resistant Stainless Steel Enclosure (30 & 60A)



Amps	Type	Dim. Ref.	A	B	C	D	E	F
30	Fused & Non-fused	A1, A2	305 (12.00)	305 (12.00)	173 (6.80)	224 (8.81)	267 (10.5)	267 (10.5)
60	Fused & Non-fused	B1, B2	305 (12.00)	305 (12.00)	173 (6.80)	224 (8.81)	267 (10.5)	267 (10.5)


Type 4/4X - Corrosion Resistant Non-Metallic Enclosure (30 & 60A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Amps	Type	Dim. Ref.	A	B	C	D	F	G	H	J	K
30 & 60	Fused & Non-Fused	A1 & A2 B1 & B2	226 (8.92)	267 (10.52)	163 (6.42)	214 (8.43)	278 (10.95)	152 (6.0)	216 (8.50)	305 (12.0)	6 (0.23)


Type 4/12 Metallic and Type 4/4X Stainless Steel Enclosure (100A)



Amps	Type	Dim. Ref.	A	B	C	D	E	F
100	Fused & Non-fused	C1	406 (16.00)	406 (16.00)	224 (8.80)	282 (11.10)	368 (14.5)	368 (14.5)


Type 4/12 Metallic and Type 4/4X Stainless Steel Enclosure (200 & 400A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Amps	Type	Dim. Ref.	A	B	C	D	E	F	G	H
200	Fused & Non-Fused	D1	406 (16)	610 (24)	224 (8-51/64)	282 (11-5/64)	688 (27-5/64)	650 (25-19/32)	368 (14-1/2)	572 (22-1/2)
400	Fused & Non-Fused	F1	610 (24)	762 (30)	326 (12-51/64)	384 (15-5/64)	840 (33-5/64)	802 (31-15/32)	572 (22-1/2)	724 (28-1/2)


Type 4/4X Corrosion Resistant Non-Metallic Enclosure (100A)



Amps	Type	Dim. Ref.	A	B	C	D	F	G	H	J	K
100	Fused & Non-Fused	C1	380 (14-31/32)	420 (16-1/4)	215 (8-31/64)	273 (10-49/64)	430 (16-61/64)	305 (12)	370 (14-9/16)	457 (18)	5 (13/64)


Type 4/4X Corrosion Resistant Non-Metallic Enclosure (200A)

Dimensions are in millimeters (inches). Dimensions not intended for manufacturing purposes.



Amps	Type	Dim. Ref.	A	B	C	D	F	G	J	K
200	Fused & Non-Fused	D1	513 (20-13/64)	625 (24-5/8)	292 (11-31/64)	350 (13-25/32)	648 (25-1/2)	457 (18)	686 (27)	11.5 (29/64)

Type 4/4X Corrosion Resistant Non-Metallic Enclosure (400A)



Amps	Type	Dim. Ref.	A	B	C	D	F	G	J	K
400	Fused & Non-Fused	F1	612 (24 1/8)	775 (30 33/64)	343 (13 31/64)	401 (15 23/32)	796 (31 31/32)	555 (21 7/8)	834 (32 27/32)	10.5 (13/32)